AD-A134 053 A COMPUTATIONAL PROCEDURE FOR THE PROTECTION OF INDUSTRIAL POWER SYSTEMS(U) PENNSYLVANIA STATE UNIV UNIVERSITY PARK DEPT OF ELECTRICAL ENGINEERING 1/2

UNCLASSIFIED C N SALMOND NOV 81 F/G 10/2 NL





The Pennsylvania State University

The Graduate School

Department of Electrical Engineering

A Computational Procedure for the Protection of Industrial Power Systems

A Thesis in

Electrical Engineering

by

Charles N. Salmond

Submitted in Partial Fulfillment
of the Requirements
for the Degree of

Master of Science

November 1981

We approve the thesis of Charles N. Salmond.

Date of Signature:

10-23-81 — Fredrick C. Trutt

Fredrick C. Trutt, Associate Professor of Electrical Engineering, Thesis Adviser

10-23-81 — [signature]

Dale M. Grimes, Head of the Department of Electrical Engineering

10-22-81 — Lloyd A. Morley

Lloyd A. Morley, Professor of Mining Engineering, Member of Thesis Committee

10-22-81 — Geo. A. Etzweiller

George A. Etzweiller, Associate Professor of Electrical Engineering, Member of Thesis Committee

ABSTRACT

A procedure is presented that allows an engineer to coordinate protective devices consisting of fuses, circuit breakers, and over-current relays based upon load and fault currents. The resulting digital-computer program makes many of the decisions requiring very little prior in-depth knowledge of protective devices and power systems for its utilization.

The coordination procedure consists of six separate programs that must run in sequence, as the output from one program forms the input for the next program. This reduces in size of internal computer storage required.

The theory is presented with an explanation of each algorithm followed by a basic flow chart. An example computer run is presented at the end.

TABLE OF CONTENTS

Page

LIST OF TABLES

LIST OF FIGURES

ACKNOWLEDGMENTS

The author is indebted to Dr. Fredrick Trutt and Dr. Lloyd A. Morley for their support and guidance throughout this thesis project.

Dr. William S. Adams and his staff of technicians in the Electrical Engineering Hybrid Computer Laboratory, Mr. John Griebling, and Mr. Robert Hirlinger were especially helpful.

The author appreciated the comments and suggestions of Dr. George A. Etzweiler in his critical review of this work.

1. INTRODUCTION

A prime objective of electrical engineers working on the design, operation, or maintenance of electrical power systems is to provide reliable, efficient power to their customers. The distribution system has always been a weak link in the power chain. Often, the catastrophic results of a fault are easily seen, but the cause may be extremely difficult to find. A distribution system, either in the utility or the user's facilities that is not adequately protected from electrical faults is both dangerous and costly. An unsatisfactorily protected system can cause considerable inconvenience and damage to equipment. Adequate protection is not a set definition. Each load system is different with its own set of boundary values.

In a distribution system, the flexibility of design reduces near the generator or the load. Usually the generator or load protection is designed as an integral part of the equipment by the manufacturer and any changes should only be undertaken with their counsel. Moving away from the generator or load, the priority shifts from load protection to distribution protection. It must never be forgotten that the load, distribution, and generation systems must be protected in such a way that a device that operates satisfactorily in one system cannot have a detrimental effect on another system. In this thesis the distribution section is attached from an infinite-bus power source to the load-protection device. The programs provide the

proper setting of a chosen device in order to provide good protective coordination. Proper coordination is achieved when a device closest to the fault clears the fault or overload condition before the rest of the system is disturbed. In order to achieve this end by manual means, extensive mathematical calculations and experience are required. As a direct result, proper coordination is often not achieved. The use of digital computers to solve the coordination problem makes a more exacting solution. However, computers with large internal memory are required to solve these problems. Several approaches to computer solutions have been published [1-4].

Problem Statement

The purpose of this thesis is to develop the procedure and an interactive computer program for a generalized case of device coordination. This coordination should include fuses, relays, and molded case circuit breakers. The phases of research are as follows.

1. Develop a computer procedure to compute the one-line program per unit values.

2. Develop a computer procedure to perform a load-flow analysis.

3. Develop a computer procedure to compute line-to-line ground and three-phase faults.

4. Develop and apply p...du... for mathematical representation of line X/R data, fuse, molded-case circuit breaker, and relay-curve time-current characteristics.

5. Develop a computer procedure to coordinate the devices from phase 4 with the data derived from phases 2 and 3.

Although the coordination programs are written for the PDP10 computer, it requires no more than 25K bytes of internal memory and a disk unit to solve any system of 30 buses and 100 elements. Almost any large system can be reduced to its smaller parts composed of 30 buses or less. As each segment is coordinated, it can be represented by a load and its protective device. In this manner a 300-bus system could be divided into smaller segments and in 11 runs would be completely coordinated. The step-by-step approach used here allows for insertion or extraction of data before proceeding to the next step. Figure 1.1 is a basic flow chart of the coordination program. Hereafter it will be referred to by its individual parts.

When the coordination process has been completed, a load flow study and a fault analysis has been performed as well. The major assumptions that have been made are listed here. Other minor ones are included in the corresponding chapters. These assumptions have been made in an effort to keep the solution as general as possible.

1. The incoming line is assumed to be an infinite bus.

2. Assymetrical currents are neglected. Devices are coordinated on the basis of symmetrical fault currents.

3. Only synchronous-motor contributions to the fault currents are recognized. If a large induction motor



Figure 1.1. Flow chart of the coordination procedure.



Figure 1.1. Continued.



Figure 1.1. Continued.

is present, it may be added as a fictitious synchronous motor.

4. Line-charging shunt admittance is ignored.

5. Prefault current and voltages are neglected in fault-current computations.

6. Different sizes of fuses have the same time-current curve shape.

7. Overload conditions are 125% of full load.

8. The system has a balanced three-phase load.

In this thesis each phase of research in the problem statement has a chapter devoted to it. After describing the computational methods used in curve smoothing, the coordination problem begins with data input. Next the fault currents are solved followed by the actual coordination program and device response graphing. Finally, a sample distribution system coordination problem is described.

2. CURVE SMOOTHING AND DIGITIZING

General

In this chapter, the methods for using a data digitizing "numonics" device and the curve smoothing program of Appendix A are explained. The various device equations that were found that adequately represented the particular device's time current curve are also described.

A method was described in Wagner [1] for performing this by using the PDP10 computer. This least-square curve-fitting program [1] was expanded to eliminate any external subroutines that may not be available. The coordination program makes extensive use of polynomial functions whose coefficients were derived by using the least-squares curve-smoothing technique.

Curve Smoothing

Electrical Cables. Coefficients for the mathematical modeling of resistance and reactance were taken from data for mine power cable [5]. This is used as only one type of cable or wire. Any other type may be modeled by the same procedure. For instance, either actual cable or line data could be used directly [6], or the theoretical resistance and reactance for each size could be calculated [5-8].

Fuses. Two types of fuses are used in the coordination program. These are current-limiting and solid-material boric-acid power fuses. In each case, the curve shape is assumed to be the same for different sizes. The low-current asymptotic value is called the "ofset." Each fuse has a minimum and a typical operating time. In fuse coordination, both values must be used in describing the operating envelope of a particular fuse. The higher typical operating time curve is referred to as "Ofset 1." By this means, any fuse can be completely described by four equations, where:

$$\text{Log } T_{min} = \left(\sum_{j=o}^{n} a_j (\text{Log Current} - \text{Ofset})^j \right) - 2 \qquad (2.1)$$

$$\text{Log } T_{yp} = \left(\sum_{k=0}^{n} a_k (\text{Log Current} - \text{Ofset1})^k \right) - 2 \qquad (2.2)$$

Fuses are selected also by using mathematical models. To select a fuse, the program uses the overload-current value as the variable in the polynomial function. The result is the device number. In curve smoothing, variables can assume no value less or greater than those originally used as data for the curve-smoothing program, or large errors can result.

Molded-Case Circuit Breakers. Like the fuses discussed above, each molded-case circuit breaker consists of an operating envelope bounded by a minimum value and a maximum value. Unlike fuses, however,

a table look-up approach is used in selection of a device and its setting because of the smaller number of sizes and magnetic-trip settings.

Relays. Wagner [1] discusses the representation of the family of relay curves for each type with one polynomial equation comprised of four coefficients. The 0^{th} power coefficient was left out as a variable for coordination. Unfortunately, this method proves unsatisfactory when working with more than one relay type. It was found that each relay could be represented by five coefficients. The 0^{th} power coefficient is necessary in that it provides the time displacement necessary for minimum time dial setting. The curves were derived using the procedure below.

Westinghouse Company type relays were used. An average curve was taken as time-dial 4. This curve was reduced to a polynomial function. The time difference between time-dial 4 and time-dial 1/2 taken at 20 times the pickup value is subtracted from the 0^{th} coefficient. Twenty times pickup was a good value for computing the time difference as the time value changes very little for increases in current beyond that point. The resultant curve was the average shape of a time-dial setting of 4 now shifted to minimum setting. This allows for time values computed during coordination to be summed with the 0^{th} coefficient. The curves are then represented as follows:

$$\text{Log Time} = \left(\sum_{j=0}^{n} a_j (\log(\text{Current Value})^j\right) + \log(\text{Time Setting})$$

This allows the use of more than one type of relay in each coordination as it separates time setting value from relay type.

Curve Digitizing. The device's time versus current curves were digitized by using a NUMONICS electronic graphics calculator (EGC). The NUMONICS EGC is designed to translate graphic information on any medium into digital information. Complete information on its usage may be found in -NUMONICS Electronic Graphics Calculator [9]. The NUMONICS EGC then provided a convenient way to enter X-Y coordinate data representing any curve onto disk. Since this device works in length in inches, the data has to be normalized to its proper units.

A simple program DIGIT.F4 was written to normalize and store onto disk the NUMONICS EGC information. The program flow chart is shown in Figure 2.1.

Curve Smoothing. The curve-smoothing program contained in Wagner [1] was used as a basis for the curve smoothing program DEV.F4. Unnecessary parts were removed and a double precision matrix inversion routine was added. This prevented the necessity of using subroutines contained in the computer's SSP routine files. The inversion routine was converted from The Pennsylvania State University Computer Center's matrix inversion routine CMINV which inverts a complex square matrix. This routine in turn was converted from the SSP routine MINV [10].

Since it has its own inversion routine, this curve smoothing program can be easily expanded to any number of points and any dimension of fit by changing the dimension statements. The flow chart and procedure remains the same as in [1]. A complete program listing may be found in Appendix A.



Figure 2.1. Curve-digitizing flow chart.



Figure 2.1. Continued.

Summary

Polynomial functions describe the various device-response curves, line X/R data, and fuse-selection criteria. The coefficients for these polynomial functions are found from data entered using a digital-data device or manual input. This data is reduced by a curve-smoothing program to the desired function.

The start of the coordination problem begins in the next chapter with line and load data entry.

3. THE INPUT OF DISTRIBUTION-SYSTEM DATA

General

Usually, the first step in performing any calculations on a distribution system is to reduce all system values to per unit. The methods used to do this in the program will be described in this chapter. Errors can be introduced easily when converting to the per unit system using manual calculations. Program INPUT.F4 was written to perform this function as well as computing line resistance and reactance values and storing all system data on disk for use in subsequent programs.

Per-Unit Reduction

The program uses the following formulas to convert to the per-unit system [8]. (See Table 3.1 for variable definitions used in this thesis.)

$$Z_{Base} = (KV_{Base})^2/MVA_{Base}$$

$$Z_{P.U.} = Z(\Omega)/Z_{Base}$$

$$I_{Base} = KVA_{Base}/KV_{Base}$$

Table 3.1. Variable definitions.

$Z(\Omega)$	element impedance
$Z_{P.U.}$	impedance in per unit
X_d	subtransient reactance
P_p	real power bus p
Q_p	reactive power bus p
E_p	complex voltage bus p
I_p	complex current bus p
Y_{pq}	Y bus element bus p to q
$\bar{y}_{pq,rs}$	admittance value from primitive admittance matrix
Z_{pq}	Z bus element bus p to q
$z_{pq,pq}$	impedance value from primitive impedance matrix
z_f	fault impedance
y_f	fault admittance

$$Z_{P.U.new} = Z_{P.U.given} \left(\frac{KV_{Base\ given}}{KV_{Base\ new}}\right)^2 \left(\frac{KVA_{Base\ new}}{KVA_{Base\ given}}\right)$$

Utilizing the above formulas it is possible then to represent all elements in the distribution system on a per-unit basis. Loads need to be included also in the one-line representation.

The program allows loads to be represented either by induction motor horsepower, synchronous motor horsepower, kVA, or current.

Loads are entered in the following format: Bus number/horsepower, kVA, current/power factor. The program assumes 100% efficiency so one must use:

$$HP_{Entered} = HP/Efficiency \tag{3.1}$$

If information on efficiency and power factors are unknown, the following equations may be used instead of 3.1 [9].

For induction motors, use:

$$HP_{Entered} = HP \times 1.1627$$

$$\text{Power Factor} = .86 \tag{3.2}$$

For synchronous motors use:

$$\text{Unity Power Factor HP} = 1.139 \times \text{Horsepower} \tag{3.5}$$

$$.8 \text{ Power Factor HP} = 1.18 \times \text{Horsepower} \tag{3.6}$$

Formulae for Line Resistance and Reactance

Element data is entered in the following format: line bus/ load bus/cable length in feet/wire size/transformer P.U. impedance/ size in MVA/line voltage in KV/load voltage in KV.

Wire sizes that are entered in American wire gauge (AWG) are converted to MCM wire gauge by using the following formula [1]:

$$MCM = [(.005)[(1.229)^{(36\ AWG)}]^{2} \times 1000 \qquad (3.7)$$

Once the wire size is in MCM, the line resistance and reactance are computed using the polynomial coefficients that were found by the procedure in Chapter 2.

$$\text{Resistance or reactance} = \sum_{j=0}^{n} a_j [\log(MCM)]^j \qquad (3.8)$$

The program should not be limited to just one wire type. The program does this by reading wire coefficients a_j above from disk so that each time the program is run it can compute element data using different wire types until the entire system has been completely entered.

Transformers become very important in that they can become the highest source of resistance and reactance. By their connections and neutral impedance, they determine the magnitude of zero-sequence current that will flow in the particular element. The program allows for this input and writes this information in the particular disk files for use later on in fault analysis.

Transformer inrush and withstand values must also be calculated. These values must be used in coordinating protective devices. These devices must pass inrush currents but open under conditions of exceeded transformer withstand currents. The algorithm in the program is based on average values. If test data is available this should be entered directly by changing the transformer data disk file directly after the program is run and before proceeding with coordinations. Inrush and withstand values are computed as follows [11]:

$$\text{Inrush} = 12\text{x}(\text{Transformer Base Current}) \tag{3.9}$$

$$\text{Withstand @2 Sec} = 25\text{x}\ (\text{Transformer Base Current}) \tag{3.10}$$

$$\text{Withstand @5 Sec} = 14.5\text{x}\ (\text{Transformer Base Current}) \tag{3.11}$$

Transformer withstand is some value between the two second value to the five second value and depends upon the transformer impedance. It is fairly easy, however, to have the device protect the complete range of withstand values and the program is written to accomplish this task.

Synchronous subtransient reactance is computed as follows [11]:

$$(\text{Per unit KVA}) \times (.17) = jX_d \tag{3.12}$$

One of the problems encountered in computing transmission line impedance is a reasonable calculation of the zero-sequence impedance. The computer program assumes that this value is two times the positive-sequence impedance [8] if nothing is entered when the computer asks for the zero-sequence impedance multiple. If a different value is entered, the computer multiplies the positive sequence reactive value by this multiple to arrive at the zero-sequence value.

A basic flow chart follows in Figure 3.1 with a complete program listing in Appendix B.

Summary

The first step toward solving the coordination problem is completed. All element data has been converted to the per-unit representation. The next logical step is to perform a load-flow analysis to determine the full load currents in each element.

Flow Chart Input



Figure 3.1. Per-unit calculations flow chart.



Figure 3.1. Continued.

4. LOAD-FLOW ANALYSIS

General

In order to establish overload conditions on each element, the load currents must be determined. This is done by using a load flow analysis. The Newton-Raphson Method using Y-bus [12] was chosen because it required the least amount of iterations to obtain a solution to the load-flow problem.

Load Flow

In this method Y-bus must first be formed from the primitive-impedance network. When mutual coupling is ignored, Y-bus can be formed easily by algorithm. Any system can be completely represented by a set of equations [8,12].

$$I^{bus} = (Y^{bus})(E^{bus}) \tag{4.1}$$

E^{bus} and I^{bus} are column matrices with one entry for each bus in the system. Y^{bus} is a square matrix of order equal to the number of buses in the system. Therefore, once all bus voltages are known and Y-bus is formed, matrix multiplication gives the desired load currents.

However, there is no direct approach to obtain the bus voltages. The only approach to use is that of iteration. The Newton-Raphson method accelerates the iteration process so that normally an accurate answer is obtained after three iterations.

The power at bus p is (from 4.1):

$$P_p - jQ_p = E_p^* I_p$$

$$P_p - jQ_p = E_p^* \sum_{q=1}^{n} Y_{pq} E_q \tag{4.2}$$

$$E_p = e_p + jf_p \quad Y_{pq} = G_{pq} - jB_{pq} \tag{4.3}$$

So

$$P_p = \sum_{q=1}^{n} \{e_p(e_q G_{pq} + f_q B_{pq}) + (f_q G_{pq} - e_q B_{pq})\} \tag{4.4}$$

$$Q_p = \sum_{q=1}^{n} \{f_p(e_q G_{pq} + f_q B_{pq}) - e_p(f_q G_{pq} - e_q B_{pq})\} \tag{4.5}$$

The Newton-Raphson method uses the Jacobian matrix of partial-differential equations as follows:

$$\begin{bmatrix} \Delta P_1 \\ \Delta P_{n-1} \\ \hline \Delta Q_1 \\ \Delta Q_{n-1} \end{bmatrix} = \left[\begin{array}{ccc|ccc} \frac{\partial P_1}{\partial e_1} & \cdots & \frac{\partial P_1}{\partial e_{n-1}} & \frac{\partial P_1}{\partial f_1} & \cdots & \frac{\partial P_1}{\partial f_{n-1}} \\ \frac{\partial P_{n-1}}{\partial e_1} & \cdots & \frac{\partial P_{n-1}}{\partial e_{n-1}} & \frac{\partial P_{n-1}}{\partial f_1} & \cdots & \frac{\partial P_{n-1}}{\partial f_{n-1}} \\ \hline \frac{\partial Q_1}{\partial e_1} & \cdots & \frac{\partial Q_1}{\partial e_{n-1}} & \frac{\partial Q_1}{\partial f_1} & \cdots & \frac{\partial Q_1}{\partial f_{n-1}} \\ \frac{\partial Q_{n-1}}{\partial e_{n-1}} & \cdots & \frac{\partial Q_{n-1}}{\partial e_{n-1}} & \frac{\partial Q_{n-1}}{\partial f_1} & \cdots & \frac{\partial Q_{n-1}}{\partial f_{n-1}} \end{array}\right] \begin{bmatrix} \Delta e_1 \\ \Delta e_{n-1} \\ \hline \Delta f_1 \\ \Delta f_{n-1} \end{bmatrix}$$

$$\begin{bmatrix} \Delta P \\ \hline \Delta Q \end{bmatrix} = \left[\begin{array}{c|c} J_1 & J_2 \\ \hline J_3 & J_4 \end{array}\right] \begin{bmatrix} \Delta e \\ \hline \Delta f \end{bmatrix} \tag{4.6}$$

The elements of the Jacobian matrix are found from the following equations:

$$J_1: \quad \frac{\partial P_p}{\partial e_q} = e_p G_{pq} - f_p B_{pq} \quad q \neq p$$

$$\frac{\partial P_p}{\partial e_p} = 2e_p G_{pp} + f_p B_{pp} - f_p B_{pp} + \sum_{\substack{q=1 \\ q=p}}^{n} (e_q G_{pq} + f_q B_{pq}) \tag{4.7}$$

$$J_2: \frac{\partial P_p}{\partial f_q} = e_p B_{pq} + f_p G_{pq} \quad q \neq p$$

$$\frac{\partial P_p}{\partial f_p} = e_p B_{pp} + Z_{fp} G_{pp} - e_p B_{pp} + \sum_{\substack{q=1 \\ q \neq p}}^{n} (f_q G_{pq} - e_q B_{pq}) \tag{4.8}$$

$$J_3: \frac{\partial Q_p}{\partial e_q} = e_p B_{pq} + f_p G_{pq} \quad q \neq p$$

$$\frac{\partial Q_p}{\partial e_p} = f_p G_{pp} - f_p G_{pp} + Z_{ep} B_{pp} - \sum_{\substack{q=1 \\ q \neq p}}^{n} (f_q G_{pq} - e_q B_{pq}) \tag{4.9}$$

$$J_4: \frac{\partial Q_p}{\partial f_q} = e_p G_{pq} + f_p B_{pq} \quad q \neq p$$

$$\frac{\partial Q_p}{\partial f_p} = e_p G_{pp} + Z_{fp} B_{pp} - e_p G_{pp} + \sum_{\substack{q=1 \\ p \neq q}}^{n} (e_q G_{pq} + f_q B_{pq}) \tag{4.10}$$

Bus #1 or the swing-bus voltage is known. The swing bus is the bus that will provide whatever power the system requires. The program begins by forming Y-bus by using the primitive-impedance matrix generated by INPUT.F4 of Chapter 3. Since mutual coupling is ignored, the y-admittance matrix can be found by inverting each member of the z-impedance matrix found in disk file TEST.DAT. Y^{bus} matrix is formed using the algorithm below.

Diagonal elements are formed as the sum of all admittances connected to that bus or node. Off-diagonal elements are the negative of the admittance connected between the buses or nodes.

If more than 10 iterations are performed, the program stops and informs the user that either an error has been made in design or data entry. Upon successful completion of the program, a load-flow analysis may be obtained by printing file *DISK.DAT*. The program puts the load currents in the proper format and file for later use in the coordination program. A flow chart follows in Figure 4.1, and a complete listing is given in Appendix B.

Summary

This load-flow analysis obtained can be very useful in analyzing the distribution-system design. It can be used to point out locations for power factor correction as well as potential problems due to under-sized wiring.

The load currents found here are stored on disk to be used in the coordination program. The next step before beginning the

coordination program is to solve for all fault currents. Z-bus must be formed to compute these currents. The methods used to do this follows in the next chapter.



Figure 4.1. Newton-Raphson load-flow chart.

5. FORMATION OF IMPEDANCE-BUS NETWORK

General

The formation of the impedance bus network ($Z\text{-}Bus^{012}$) by algorithm is the first step toward solving for fault currents. In this chapter this algorithm will be discussed as well as other problems encountered in matrix compression.

Formation of Z-Bus

Once the one line diagram has been completed, the primitive impedance matrix that was found in INPUT.F4 is a partially filled matrix. However, it is not in the proper format for the formation of Z-bus as it contains no coupling. The primitive impedance matrix must change from one of order equal to the number of buses to one of order equal to the number of elements. This matrix becomes a very large sparse matrix. The memory required to store this matrix becomes too large to fit in a small computer. A method was derived to only store the non zero values and their location in the matrix. Since the matrix is triangular only the top half is stored (Figure 5.1).

Diagonal elements found in INPUT.F4 are stored in "ZD." ZD is a three-dimensional matrix, ZD(200,2) where (X,1) is the element number and (X,2) is the diagonal value.



Figure 5.1. Transformation of square sparse primitive impedance.

The off diagonal mutual coupling Zm is a three dimensional matrix also where (X,1) is the location value A+jB. Element A is coupled to element B. Location (X,2) is the coupling value. Fortunately, partitioning makes it necessary to assemble a square matrix for inversion of only the coupled elements. Since coupling only exists in zero sequence, this applies only to the zero-sequence Z-bus matrix.

In the formation of the Z-bus matrix, bus 1 is the reference bus for all calculations. Z-bus is formed by starting with element one and proceeding with each element in turn. An element is either a link or branch. A link means that both buses have been used earlier; a branch means they have not been used earlier.

Like Y-bus in Chapter 4 any system can be represented by

$$Ebus^{012} = Zbus^{012}\ Ibus^{012}$$

Formation of $Zbus^{012}$ can be formed either by the incidence, network-matrices method [12] or by algorithm. Formation by algorithm is much simpler and is used here.

After forming the primitive impedance network, it is a straightforward application of the equations of Table 5.1.

Table 5.1. Equations for the formation of ZBUS. [11]

Add p-q	Mutual Coupling	No Mutual Coupling
Branch	$Z_{qi} = Z_{pi} + \bar{y}_{pq,rs}(\bar{Z}_{ri} - \bar{Z}_{si})$	$Z_{qi} = Z_{pi}$
	$i = 1, 2, \ldots, m$ $i \neq q$	
	$Z_{qq} = Z_{pq} + \dfrac{1 + \bar{y}_{pq,rs}(\bar{Z}_{pq} - \bar{Z}_{rs})}{y_{pq,rs}}$	$Z_{qq} = Z_{pq} + z_{pq,pq}$
Link	$Z_{li} = Z_{pi} - Z_{qi} + \dfrac{\bar{y}_{pq,rs}(\bar{Z}_{ri} - \bar{Z}_{si})}{y_{pq,pq}}$	$Z_{li} = Z_{pi} - Z_{qi}$
	$i = 1, 2, \ldots, m \quad i \neq l$	
	$Z_{ll} = Z_{pl} - Z_{ql} + \dfrac{1 + \bar{y}_{pq,rs}(\bar{Z}_{rl} - \bar{Z}_{sl})}{y_{pq,pq}}$	$Z_{ll} = Z_{pl} - Z_{ql} + z_{pq,pq}$
Elimination of 1^{th} Node		
	$Z_{ij}(\text{modified}) = Z_{ij}(\text{before elimination}) - \dfrac{Z_{il} Z_{lj}}{Z_{ll}}$	
	$i,j = 1, 2, 3, \ldots, m$	

For example, a primitive impedance matrix looks like this for five elements:

$$z^o = \begin{array}{c} \\ 1 \\ 2 \\ 3 \\ 4 \\ 5 \end{array} \begin{array}{c} \begin{array}{ccccc} 1(1\text{-}2) & 2(2\text{-}3) & 3(3\text{-}4) & 4(1\text{-}4) & 5(2\text{-}4) \end{array} \\ \begin{bmatrix} .1+j.5 & j5 & & & \\ j5 & .1+j.5 & & & \\ & & .1+j.5 & j10 & j4 \\ & & j10 & .1+j.5 & j8 \\ & & j4 & j8 & .1+j.5 \end{bmatrix} \end{array} \quad y^o = [z^o]^{-1}$$

where the off diagonal values represent mutual coupling between elements. Using this primitive matrix and the equations in Table 5.1 yields Zbus.

ZBUS.F4 is one of the longest programs in the series. The program asks for the zero-sequence impedance for all loads in the system and the mutual-coupling impedances. If the zero-sequence impedance of a load is not known, the program assigns it the same value as the positive sequence impedance.

All loads that are added are links, and only loads that are added are those of synchronous motors. The subtransient reactance is used instead of its actual impedance since the Z-bus is going to be used for fault calculations. Any link from a bus to the reference bus will cause a fault current. Prefault voltages and currents will be ignored as will all contributions from loads other than synchronous motors. A flow chart follows (Figure 5.2) and a complete program listing in Appendix B.



Figure 5.2. Zbus[012] formation flow chart.



Figure 5.2. Continued.



Figure 5.2. Continued.

Summary

$Zbus^{012}$ is formed by algorithm allowing for mutual coupling between elements. The next step in the coordination procedure is to solve for fault currents. This procedure follows in the next chapter.

6. FAULT CALCULATIONS

General

The final program required before executing the coordination program is FALT.F4. This program computes all the possible line-to-ground and three-phase-fault currents and prepares all other load data for entry into the coordination program. The procedure to accomplish this will be discussed in this chapter.

Fault Currents. The equations describing the fault currents need to be derived [12].

Three-Phase Fault. For a fault at bus P:

$$I_{P(F)}^{012} = Y_F^{012}(U+Z_{pp}^{012}Y_F^{012})^{-1}E_{P(0)}^{012} \tag{6.1}$$

where U is unity matrix, $E_p(0)$ is prefault voltage, and Y_F is the fault admittance matrix for a three-phase fault.

$$Y_F^{012} = y_F \begin{bmatrix} 0 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \tag{6.2}$$

Substituting (6.2) into (6.1)

$$I^{012}_{P(F)} = y_F \begin{bmatrix} 0 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1+Z^{o}_{pp} & & \\ & 1+Z^{1}_{pp}y_f & \\ & & 1+Z^{2}_{ppf} \end{bmatrix}^{-1} \begin{bmatrix} 0 \\ \sqrt{3} \\ 0 \end{bmatrix}$$

$$I^{012}_{P(F)} = y_F \begin{bmatrix} 0 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} \frac{1}{1+Z^{o}_{pp}} & & \\ & \frac{1}{1+Z_{pp}{}^{1}y_F} & \\ & & \frac{1}{1+Z_{pp}{}^{2}y_F} \end{bmatrix} \begin{bmatrix} 0 \\ \sqrt{3} \\ 0 \end{bmatrix}$$

$$I^{012}_{P(F)} = y_F \begin{bmatrix} 0 & 0 & 0 \\ 0 & \frac{1}{1+Z_{pp}{}^{1}y_F} & 0 \\ 0 & 0 & \frac{1}{1+Z_{pp}{}^{2}y_F} \end{bmatrix} \begin{bmatrix} 0 \\ \sqrt{3} \\ 0 \end{bmatrix} \qquad (6.3)$$

Since $Zpp^1 = Zpp^2$ and $z_f = 1/y_f$

$$I^{1}_{P(F)} = \frac{\sqrt{3}}{z_F+Z_{pp}} \quad I^{0}_{P} = 0 \quad I^{2}_{P} = 0 \qquad (6.4)$$

Using the same method the following equations are found [12].

$$E^{1}_{P(f)} = \frac{\sqrt{3}\, z_F E_{Po}}{z_F + Z_{PP}^{1}} \tag{6.5}$$

and

$$E_{i(F)}{}^{1} = \sqrt{3}\,(E_{i(0)} - \frac{Z_{ip}^{(1)} E_p(0)}{z_f + Z_{pp}^{(1)}}$$

$$i \neq P \quad E_i{}^{0,2} = 0 \quad E_{p(f)}{}^{0,2} = 0 \tag{6.6}$$

These equations are identical to those found for a three-phase grounded fault [12].

The line-to-ground fault admittance matrix is given by $Y_F{}^{012}$ below. Substituting $Y_F{}^{012}$ into (6.1) the equations below result [12].

$$Y_F^{012} = \frac{y_F}{3}\begin{bmatrix} 1 & 1 & 1 \\ 1 & 1 & 1 \\ 1 & 1 & 1 \end{bmatrix}$$

$$I_P{}^{012} = \frac{\sqrt{3}\, E_{p(0)}}{Z_{pp}^{0} + 2Z_{pp}^{(1)} + 3z_F} \tag{6.7}$$

$$E_p^{012} = \frac{\sqrt{3}\, E_p^0}{Z_{pp}^{(0)} + 2Z_{pp}^{(1)} + 3z_F} \begin{bmatrix} -Z_{pp}^{(0)} \\ Z_{pp}^{(0)} + Z_{pp}^{(1)} + 3z_F \\ -Z_{pp}^{(1)} \end{bmatrix} \quad (6.8)$$

$$E_{i(F)}^{012} = E_{i(0)} \begin{bmatrix} 0 \\ \sqrt{3} \\ 0 \end{bmatrix} - \frac{\sqrt{3}\, E_{p(0)}}{Z_{pp}^{(0)} + 2Z_{pp}^{(1)} + 3z_F} \begin{bmatrix} Z_{ip}^{(0)} \\ Z_{ip}^{(1)} \\ Z_{ip}^{(1)} \end{bmatrix} \quad (6.9)$$

$i \neq p$

The value of z_F is entered from the keyboard when asked by the program. All of the equations are available now to solve for all fault currents. All post-fault bus voltages are solved. Using these bus voltages each element fault current is determined. These currents are stored onto disk so that they may be used in both the coordination and graphing programs.

Summary

The programs thus far have solved for all load and fault currents but no coordination has been discussed. Now the coordination problem is ready to be addressed. In the chapter that follows, the protective devices for the distribution system will be coordinated.



Figure 6.1. Flow chart for FALT.F4.

7. PROTECTIVE-DEVICE COORDINATION

General

In this chapter, the protective-device-coordination problem will be discussed. A computational method is put forward that allows a digital computer to solve the problem.

Device Coordination

One of the best methods to approach coordination is a step by step device selection and setting working from the load toward the source. A load is the best place to start because there is not much flexibility for device setting at a load. The load flow analysis of Chapter 4 provides the overload values for the various loads. This enables a definite overload setting for each device protecting a load. Since overload currents are a primary concern at these buses, all fault settings can be placed at six times the full load currents. This should allow for normal starting currents. Care must be taken so that an instantaneous tripping element will not open under normal starting conditions. From the loads it is a straightforward process to place a line side device curve next to its load side curve to insure that proper coordination is achieved. By taking this approach, each device depends only on one other device.

This program is written with the option of entering two devices in each element--one located at each bus. From this approach, obviously two possibilities can occur. Either the device is on the line side of the element or on the load side of the element (Figure 7.1). If it is the line-side device, its setting depends only on the one load-side device. It must be coordinated for the fault current at the load bus and not the line bus [1]. Devices must be coordinated for a minimum possible fault current which will be discussed later.

If the device is on the load side and it does not protect a load, then it must protect a following bus. This device must then be coordinated with all line-side devices connected to the bus it protects. This load-side device must be coordinated for fault currents at the protected bus.

Devices should be set to (1) open under overload conditions, (2) open under minimum fault conditions with proper coordination, and (3) open under maximum fault conditions with proper coordination. Often, however, all three conditions cannot be met simultaneously unless the proper devices are chosen. Criterion (1) is not as important as Criterion (2) or (3) when in the distribution system not at a load bus since an overload condition below fault conditions should not do damage to the wiring. For this reason wire sizes must be checked to insure that upon final coordination they can withstand the overload and fault conditions that can occur [5,13]. At this point it may be necessary to begin the entire coordination procedure again if an element cannot withstand the short-circuit conditions. Allowable short-circuit currents can be checked by using the final coordination graph and the fault currents obtained in FALT.F4.



(a) Coordinating line side device of an element.



(b) Coordinating load side device of an element feeding a bus with load elements connected W, Z. Y.

Figure 7.1. Two possibilities for coordination element Z. In Figure (7.1a) coordination device A according to curve device B up to fault bus 2. In Figure (7.1b) coordination device B depending on load flow current element Z. Coordinated with device curves C, D, E, up to fault at Bus 2.

This coordination routine utilizes fault currents and load currents in achieving protective-device coordination. The load currents determine the overload or pickup setting in each device. The coordination problem is then in two parts.

Devices must be coordinated for overload conditions. This provides the most important coordination step for fuses in that they contain no variable fault-protection settings as do relays or molded-case circuit breakers. Also, another reason is that based upon only fault currents and load-side device settings, it is impossible to satisfactorily achieve coordination.

This inability to achieve coordination enters when setting a device that is to protect a bus with other elements attached to that bus as loads. Just laying a line curve next to a load curve with the highest time value at any current value will provide an erroneous answer. This device must be set by determining its overload current value first since this current is the sum of all currents in the load elements that are attached to that bus. Once this point has been established, each load device curve must be polled in turn to insure that the device setting responds to a fault in a load element slower than the load element line side device. The device needs to be coordinated up to the maximum fault current that the device will see. It is possible for this device to see a smaller fault current than that in a load element.

Coordinating a device located at a line-side bus is much simpler since the pickup or overload setting is the same as the load-side device. The line-side device must be coordinated up to the maximum

fault current that will occur at the bus where its load-side device is located. A higher fault current will occur the closer one gets to the line-side device; however, this higher current value will only cause the line-side device protecting the element to respond quicker. The method of coordination will be to first find a load point based on a load flow, and second coordinate the device at any current value up to some maximum fault current such that the line-side device has a longer response time than its load-side device.

Since the program coordinates three different types of devices, nine different possibilities can occur. Each device may be coordinated with one of its own type or one of the other two.

The program structure lends itself well to the use of subroutines. Two of these are SELECT and SETDEV. SELECT chooses a device and sets its own load point, and SETDEV coordinates it.

Fuse Selection and Coordination

Due to the large number of fuse sizes available, look-up tables are not as efficient as using polynomial functions to select devices. Once a load current is known, this value is substituted into one function providing the proper device number. This device number is next substituted into two other functions providing the OFSET and OFSET 1 values referred to in Chapter 2. Since there are two types of fuses in the program, current-limiting and solid-material boric-acid power fuses, there are six functions used in selecting fuses. These all have the following form:

$$Y = \sum_{j=0}^{n} a_j X^j \qquad (7.1)$$

X will be the logarithm of overload current or device number. Table 7.1 lists the various coefficients a_j.

After the fuse is selected, it must be coordinated. The program uses the values of OFSET and OFSET 1 with the applicable fuse curve to solve for a time value for a set-current value. The program searches for the load-side device to find the highest time value to that current value. If the time value is larger for the size, it is properly coordinated. If not, it increases the fuse size by one, solves for OFSET and OFSET 1, and tries again continuing until it has found the proper fuse size.

Relay Selection and Coordination

Relays provide the most difficult coordination problem. First a turns ratio for the current transformer (CT) must be chosen. The computer selects the proper tap setting to prevent saturation. It does this by always selecting the highest turns possible while selecting the tap setting on the relay as well [12]. The computation uses a 600/5 CT [13] with tap settings and CO relays [14] with tap settings. This combination of tap setting for the CT and the relay combined with the load current establish the pickup point:

$$\text{Pickup} = \text{Log}\ [(\text{Turns Ratio CT} \times \text{Turns Ratio Relay})] \qquad (7.2)$$

Table 7.1. Fuse-selection coefficients.

Current to Device		Offset	Offset 1
Current Limiting Fuses			
a_0	- 11.15221	.9532	1.1619
a_1	23.865	- .046433	- .110148
a_2	- 16.487	.117885	.10626
a_3	2.9288	- .029352	- .02249
a_4	3.19672	.00337	.002452
a_5	- 1.48877	- .0001847	- .0001365
a_6	.1776431	.0000039	.00000304
Solid Material Boric Acid			
a_0	88.1643	1.34359	1.41734
a_1	-215.2235	.151393	.1585889
a_2	188.225	- .0239735	- .035007
a_3	- 69.13403	.00046627	.007180
a_4	7.4695	.0004321	.0008126
a_5	1.65757	.0000182	- .0000377
a_6	- .347786	.0000078	0

Since relay curves are in units of multiples of pickup this pickup value will be used often. Only the relay pickup has been set, its time dial must be coordinated. Table 7.2 lists the relay-curve coefficients.

Due to the inverse time shape of a relay curve, many points on the curve must be checked with its load-side device to insure that proper coordination exists. The manner in which the family of relay curves are represented simplifies the problem somewhat. A relay operating time of 0.4 seconds is assumed throughout. At each current value, the load-side-device operating time is summed with the relay operating time. If this time is greater than the line-device time, the difference is the relay time-delay setting. Thus, when all currents up to the fault currents are checked, all points on the line-device curve are at least 0.4-seconds higher than all points on its load-side device.

Molded Case Circuit Breaker

The molded-case circuit breaker (MCCB) with its different characteristics provides a different set of problems. The MCCB curve cannot be represented by one equation. This device has one set of curves for the thermal element plus another for its magnetic element. The MCCB used in the program is a General Electric type, K-1200. Although there is some difference in the curve shape for the current ratings, 300-1200 A, they are similar enough to be represented as one type. Each MCCB has one curve corresponding to minimum total clearing time and a maximum total clearing time.

Table 7.2. Relay-curve coefficients.

	Relay Number	a_o	a_1	a_2	a_3	a_4
CO-2	1	- .4401731	-3.207952	3.098054	-1.132646	0.0
CO-5	2	1.415901	-4.556591	7.501177	-6.484299	2.233915
CO-6	3	.83421	-4.284002	7.005048	-5.298087	1.505842
CO-7	4	1.0438914	-4.308733	6.998595	-5.908597	1.894855
CO-8	5	1.7617574	-4.526460	3.226049	- .4676728	- .2548555
CO-9	6	1.476228	-2.512627	-1.278763	3.363051	-1.356438
CO-11	7	2.897519	-4.885438	4.078362	-2.517864	.7629706

The magnetic portion of the time-current curve cannot be represented adequately by a polynomial function, but is represented by:

If Current $\geq$ Magnetic Setting

Minimum Time = 0, Maximum Time = .025 seconds.

As will be seen later, .025-seconds response time is quite fast and usually does not present a problem during later coordination.

The thermal elements of molded-case circuit breakers are susceptible to temperature change so the operating temperature must be entered. The temperature merely shifts the curve to the left or right so it does not affect the curve shape. This offset is added or subtracted from the multiple of current rating when using the thermal curve polynomial functions.

The problem of coordinating the thermal elements is the same as that for fuses. The magnetic element coordination is much simpler in that the magnetic element is set separately. Its load-side device operating time is checked at a current value. If the operating time is greater, the magnetic element setting is increased. The end of the curve for the magnetic element is determined by the maximum fault current at the bus. The total decoupling of the overload from the fault device of a MCCB makes coordination much simpler than the fuse or relay. The more or less proportional-time shape of the curve will ensure that it will be properly coordinated once its proper current rating has been

established. Table 7.3 contains the polynomial coefficients used in the program.

A basic flow chart (Figures 7.2 and 7.3) follows with a complete program listing in Appendix B.

Summary

In this chapter, the coordination problem was solved to allow fuses, molded-case circuit breakers, and relays to function so as to clear a fault in the area of the fault before interrupting the rest of the distribution system. There is enough flexibility in the program to allow device settings to be changed and checked using the program PLOTD.F4. An example problem would be beneficial at this point to show how to run the programs. In the next chapter, a sample distribution system will be coordinated using the coordination programs.

Table 7.3. Molded-case circuit breaker.

$$\log(\text{time}) = \sum_{n=0}^{6} a_n [\log(\text{current}) - (\text{ofset} + .1122)]^n - 2$$

$$\log(\text{time}) = \sum_{j=0}^{6} a_j [\log(\text{current}) - (\text{ofset} + .2315)^j - 2$$

$$\text{ofset} = \log(\text{ckt breaker size})$$

Minimum Time:

$a_0 = 5.76908$

$a_1 = -10.88261$

$a_2 = 23.65418$

$a_3 = -34.7922$

$a_4 = 33.7747$

$a_5 = -21.14536$

$a_6 = 6.431778$

Maximum Time:

$a_0 = 5.8596721$

$a_1 = -4.3943349$

$a_2 = -.50690283$

$a_3 = -10.402739$

$a_4 = -17.0649561$

$a_5 = -13.011543$

$a_6 = -4.0107239$

COORD.F4



Figure 7.2. Coordination flow chart.



Figure 7.2. Continued.



Figure 7.3. Device-graphing flow chart.

8. OPERATING THE PROGRAMS

General

In this chapter the capabilities, limitations, and use of the programs will be described. The example system of Figure 8.1 will be coordinated using these programs.

One-Line Diagram

INPUT.F4. All data is entered via the keyboard in the format detailed in Chapter 3. Data entry is a straightforward process except when entering transformer data. The program is written for a "Y-Y" configuration. If one or both sides are "Δ" configured, then a large number must be entered for the transformer neutral impedance "(ZN)" on the bus connected to the Δ side. After the program is completed, the zero sequence value for the transformer element containing the transformer may be assigned an arbitrary high value if the transformer wiring is such that there can be no ground current through the element. This is done by changing its value in disk file TEST.DAT (see Appendix C for the file format).

When entering the loads the program asks which type of load to be entered. The various loads are described as:



Figure 8.1. One-line diagram of sample system.

HP - Synchronous motor
HP1 - Assynchronous motor
VA - In KVA
CUR - In amperes
S - No more loads

Load Flow

INPUT.F4. There are no entries from keyboard for this program. Printing DSK.DAT will provide a load-flow analysis in per-unit values.

Solution of Fault Currents

ZBUS.F4. In addition to forming $Zbus^{012}$, this program allows the input for mutual coupling and for zero-sequence impedance for loads. Mutual coupling tends to increase fault currents in the mutually coupled elements and small neutral-to-ground impedances can create higher line-to-ground fault currents than three-phase faults.

FALT.F4. Besides the solution of fault currents described in Chapter 6, FALT.F4 also allows the input of fault impedances. This can provide an interesting study of the system because the user can go back and place different fault impedances into the fault analysis to see if the protective devices will operate as desired.

Device Coordination and Plotting

COORD.F4. The program forms a two-dimensional complex matrix called ADEV that contains all the information required to plot all the devices in the system plus all actual settings that are to be made on the devices. An example row 3 in the matrix is 3,(3,4), (-4,2), (1.26,203), (1.03,1.26), (3,667,0), (.67,0), (20,0) in which:

1. For 3, 3 is the row location of the matrix and corresponds to the element number.

2. For (3,4), it is the first column location and is the bus numbers of the element.

3. For (4,2),-4 is a relay type #4; 2 is a current limiting fuse type #2.

4. For (1.26,203), 1.26 is the logarithm of the pickup point; 203 contains the tap information. Two is the tap of the CT, and 03 is the tap of the relay.

5. For (1.03,1.26), 1.03 is the logarithm of the current for the minimum fuse open; 1.26 is the typical fuse open point.

6. For (3.667,0), 3.667 is the magnetic setting of the relay; 0 since the fuse had no magnetic setting.

7. For (.67,0), .67 is the time-dial setting for the relay. The actual time dial setting must be read from the manufacturer's family of relay curves using the formula below at the maximum fault current.

time-dial-setting found = (found-time curve) -

(time-dial 1/2 setting)

8. For (20,0), 20 is the turns ratio of the current transformer.

Device numbers the programs asks for correspond to the devices below:

1 - Current limiting fuse
2 - Boric fuse high voltage only
3 - Molded-case circuit breaker
4 - Overcurrent relay

In device 4 the program will ask later what particular type of relay to use from Table 8.1.

Upon completion of coordination, a device listing is typed on the keyboard, and a printout of the same is available by typing: PRINT*.LPT.

When performing the plot, having a device listing as well as a fault current listing is helpful.

PLOTD.F4. This program plots the devices that were coordinated above. By using a graph, it is possible to visually check coordination. The program arrangement allows the user to change any device setting or size in ADEV.DAT to tailor the coordination to his particular requirements (see Appendix C for the file format). The program uses the lowest

Table 8.1. Overcurrent-relay types.

Program Type #	Relay Type
1	CO-2
2	CO-3
3	CO-4
4	CO-5
5	CO-6
6	CO-7
7	CO-11

Relay type numbers are listed as negative numbers by the program.

voltage in the system as a base for plotting currents. The user can select any plot offset. This has the effect of plotting only the area of concern. In this way a very detailed graph can be obtained.

Tables 8.1-8.4 provide a listing of program device type numbers to the actual device type and size.

Table 8.5 details what is contained in the various disk locations created by the programs.

To coordinate the devices in Figure 8.1, the procedure begins by entering element data using INPUT.F4. The program asks if data is to be read from disk or from the keyboard. The first element must be entered using the keyboard.

The proper procedure is to group the elements to be entered by wire or cable type as the program only handles one type of wire or cable at a time. When completed with one type, answer zero for all other questions and the computer writes the element data that it has computed on disk in the file RELA.DAT and stops. The new wire type polynomial coefficients are copied into RES.DAT and the program is ready to be run for the new wire type.

The cable coefficients used in the test problem are for mine power cable [5]. The coefficients are listed in Table 8.6.

After selecting keyboard, the base power and volts are entered. The computer then informs the user to begin element data entry. The data format (Chapter 3) is listed to aid the user. For example, the element from bus one to two of Figure 8.1 is entered as follows: 1/2/3000/6. For the element containing the 1 MVA transformer the following is input: 2/3/35/6/.001.005/1/15/4.1. The bus base voltages are

Table 8.2. Current-limiting fuses.

Program Type #	Limiting Fuses
1	5E
2	7E
3	10E
4	15E
5	20E
6	25E
7	30E
8	40E
9	50E
10	65E
11	80E
12	100E
13	125E
14	150E
15	200E

Table 8.3. Boric fuses.

Program Type #	Size
16	15E
17	20E
18	25E
19	30E
20	40E
21	50E
22	65E
23	80E
24	100E
25	125E
26	150E
27	175E
28	200E
29	250E
30	300E
31	400E
32	2-250E
33	2-300E
34	2-400E

Table 8.4. Molded-case circuit breakers.

Program #	Size
34	300 amps
35	350 amps
36	400 amps
37	450 amps
38	500 amps
39	600 amps
40	700 amps
41	800 amps
42	1000 amps
43	1200 amps

Table 8.5. Disc files.

DIGIT.F4:	Curve-smoothing program
DEV.F4:	Numonics input program
INPUT.F4	Element data-input program
LDFLO.F4:	Load-flow program
ZBUS.F4:	Formation of $ZBUS^{012}$ program
FALT.F4:	Solution of fault-current program
COORD.F4:	Coordinate device program
PLOTD.F4:	Plot device curves
RES.DAT:	Contains X/R line coefficients
TEST.DAT:	Contains element and load data in per unit
RELA.DAT:	Contains element and bus voltage data
XFOR.DAT:	Contains transformer inrush and withstand values
LOCUR.DAT:	Contains load currents
DEV.DAT:	Contains relay coefficients
DSK.XFR:	Contains load-flow currents in P.U.
DSK.DAT:	Contains load-flow analysis data
ZBUS.DAT:	Contains $ZBUS^{012}$
ZBUS.FOR:	Contains $ZBUS^{012}$ before loads are added
MUT.CO:	Contains mutual coupling data
FALT.DAT:	Contains per-unit fault currents
EFLT.DAT:	Contains per-unit fault voltages
LCUR.DAT:	Contains real values of load-flow currents
FCUR.DAT:	Contains real values of fault currents
ADEV.DAT:	Contains coordinated-device listing

Table 8.6. Mine power cable polynomial coefficients.

	R-resistance	X-reactance
a_0	0.758690526734D+01	0.6731452381407621D-01
a_1	- .1108155100578006D+02	- .1408237729509665D-01
a_2	0.6290760668063740D+01	- .1721580927352306D-02
a_3	- .1627214281565102D+01	.6845126542245339D-03
a_4	0.1604746751660286D+00	0.0

input next with the voltage in volts. Upon completion of entry of all bus base voltages, the computer types the computed element value in per unit. The load data is entered next. The program types the data entry format for the user. The 50 hp motor is entered as: 8/50/.85. The only other data to be entered are mutual coupling and zero sequence load impedance in ZBUS.F4 and fault impedance in FALT.F4. The sample problem uses no coupling and a fault impedance of zero. COORD.F4 is run next. The device type desired is entered when asked for by the program. A sample data input is given in Appendix D.

The following is a list of load locations and currents.

Bus number	Load current
4	84.0396680
4	84.0396680
7	293.6613400
8	48.9435570

The following is the current flow in the system under full load conditions as found from the load flow analysis.

Bus P	to Bus Q	Current at P	Current at Q
1	2	34.2226440	34.2226440
2	3	34.2226630	125.2048700
3	4	88.0372570	88.0372570
3	5	39.1722710	39.1722710
5	6	39.1721210	365.0129500
6	7	313.4835700	313.4835700
6	8	51.6573760	51.6573760

The following is the computed fault currents for a 3 phase fault and a line to ground fault.

Flt Bs P	Element	3 Phase	Ln to Gnd
2	1	9380.7892000	7053.9298000
2	2	261.6855700	183.7685400
2	3	677.8190200	595.4521200
2	4	280.0413400	187.2686100
2	5	280.3767000	136.2585700
2	6	2226.3547000	1496.4606000
2	7	383.7966800	270.9381000
3	1	1247.2941000	833.3620700
3	2	1247.2997000	826.2558200
3	3	846.6528100	699.4013200

Flt Bs P	Element	3 Phase	Ln to Gnd
3	4	349.8265800	206.0435600
3	5	349.7991000	204.2971400
3	6	2780.8159000	1648.7648000
3	7	479.3659400	302.5682200
4	1	1017.3596000	469.6438400
4	2	1017.3546000	466.3491300
4	3	4003.0938000	2210.2807000
4	4	285.3238800	121.9024600
4	5	285.3382800	121.3072000
4	6	2268.1567000	972.7699300
4	7	391.0159800	174.0103800
5	1	881.8973500	308.3295700
5	2	881.8899900	307.2671700
5	3	598.6094700	260.1660700
5	4	3803.2506000	1384.1725000
5	5	353.1902700	108.5970700
5	6	2807.5742000	901.2339600
5	7	483.9912400	183.8482000
6	1	791.2624200	148.9287400
6	2	791.2645000	148.4773900
6	3	537.0808000	125.4932500
6	4	3416.9009000	668.5896000
6	5	3416.8793000	569.4760500
6	6	2839.6040000	517.3090900
6	7	489.5244300	124.5511200
7	1	350.4617800	103.1131400
7	2	350.4624900	103.1008700
7	3	237.8819000	70.4041400
7	4	1513.3939000	445.7008900
7	5	1513.3895000	443.9770900
7	6	14273.8630000	4235.3970000
7	7	216.8161500	64.2673200
8	1	156.6019600	23.5717640
8	2	156.6021300	23.5401980
8	3	106.3009100	16.4766590
8	4	676.2499600	102.2285800
8	5	676.2485300	100.1874100
8	6	561.9951900	84.0780670
8	7	6769.2755000	1059.3405000

Using the device listing of ADEV.DAT and the plotted curves, it is possible to obtain all device settings.

Device number one is a molded-case circuit breaker. Its size is 300 A and its magnetic trip is on minimum setting.

Device number 10 is a current-limiting fuse number 10.

Device number 12 is a solid-material high-voltage boric fuse number 24.

The relay data follows:

Device Number	Type Number	Ct	Tap	Time Dial	Magnetic
3	1	3 (120)	7	1/2	---
4	1	3	8	8	6
5	3	3	14	5	6
6	4	3	3	4	6
7	5	3	4	6	6
8	5	3	5	6	6
9	6	3	6	10	5.2
2	1	3	13	5	5.64
11	1	3	4	10	6
13	7	3	7	2	6
14	2	3	8	1/2	6

The magnetic trip of device number 9 had to be reduced after coordination to allow the device 12 to set properly to provide protection for the 1 MVA transformer. The graphs that follow show the devices plotted to the lowest voltage in the system, 440 V. All the graphs were computer generated. The first graph shows how a one-line computer diagram would be placed to aid in understanding the graphs.



Figure 8.2. Example coordination plot.



Figure 8.2. Continued.



Figure 8.2. Continued.

Summary

The sample distribution system of Figure 8.1 was coordinated using the coordination programs. Using the device-plotting program PLOTD.F4 this coordination was checked to see if the computer generated coordination was satisfactory to the user.

During the research for this thesis, many observations were made and many features could be added to these programs in the future. This will be discussed in the chapter that follows.

9. CONCLUSIONS

In this thesis the author set out to represent a one-line distribution system in a per-unit system and to solve for three-phase and line-to-ground faults and to perform a load-flow analysis. The various protective devices-response curves needed to be represented by polynomial functions. These requirements were fulfilled using the methods detailed in Chapters 2-7.

The last task was to develop a computer procedure to coordinate a distribution system's protective devices. Fuses, molded-case circuit breakers, and relays were coordinated and their coordination graphs were plotted. There are many extensions for further work that could be done. These extensions will be discussed later.

While working with the various programs, several observations have proved useful when performing coordination. Coordination should not be an afterthought in designing a distribution system. It is easy to design a system that is impossible to coordinate correctly. A radial system is easier to coordinate. Moving from a load toward the source, the time-current curves shift to higher current-time responses so that when finally arriving at a transformer, providing proper transformer protection and coordination simultaneously may be impossible.

Coordination of the thermal-tripping elements of molded case circuit breakers is very difficult due to the difference between the minimum and maximum tripping time curves. Coordination of these

devices is best done manually with some overlap of the thermal time curves. The magnetic elements could then be adjusted to provide proper fault coordination. Those manually adjusted devices can be added to ADEV.DAT and be checked using PLOT.F4.

In systems with different voltages, the transformers should be of different sizes so that the smaller sizes are on the load side. This will allow proper coordination and protection. Relays are preferable to other types of protection on the high-voltage parts of the system in that their response can be controlled.

Recommendations for Further Work

1. Using an analog computer and the programs presented here, an entire distribution and generation system could be looked at in detail. A transient-stability study would show the effect of various device settings.

2. The INPUT.F4 program could be enlarged to automatically account for different transformer configurations.

3. Additional devices could be added easily to the program. The program allows up to twenty different relay types. The additional coefficient data is merely entered in disk DEV.DAT. Additional molded-case circuit breakers would be slightly more difficult in that it would require some program modification.

4. The plotting program could be enlarged to include drawing a one-line diagram in the space provided and adding other data directly on the graph.

5. The program could be expanded for the case of having one device in an element.

REFERENCES

1. Wagner, J. K., "Interactive Mine Power System Relay Coordination," M.S. Thesis, The Pennsylvania State University, 1980.

2. Radke, G. E., "A Method for Calculating Time Overcurrent Relay Settings by Digital Computer," IEEE Transactions on Power Apparatus and Systems, Vol. PAS-82 Special Supplement (1965): 189-205.

3. Albredt, R. E., Nisja, M. J., Feero, W. E., Rockeffeller, G. D., and Wagner, C. L., "Digital Computer Protective Device Coordination Program I--General Program Description," IEEE Transactions on Power Apparatus and Systems, Vol. PAS-83 (April 1964): 402-410.

4. Langhans, J. D. and Ronat, A. E., "Protective Devices Coordination via Computer Graphics," Proceedings of IEE Industry Applications Society Annual Meeting, October 1979, pp. 1209-1217.

5. Mining Cable Engineering Handbook, The Anaconda Company, 1977.

6. "Engineering Dependable Protection for an Electrical Distribution System," Bussman Manufacturing Division, McGraw-Edison Company, 1968.

7. Wagner, C. F., Evans, R. D., Symetrical Components, New York, McGraw-Hill, 1975.

8. Stevenson, W. D., Elements of Power System Analysis, New York, McGraw-Hill, 1933.

9. "NUMONICS Electronic Graphics Calculator," The Pennsylvania State University, Hybrid Computer Laboratory, 1976.

10. "Scientific Subroutine Package," Function "MINV," White Plains, New York, International Business Machines Company.

11. IEEE Recommended Practice for Protection and Coordination of Industrial and Commercial Power Systems. IEEE, 1975.

12. Stagg, G. W. and El-Abiad, A. H., Computer Methods in Power System Analysis, New York, McGraw-Hill, 1968.

13. Morley, L. A., Mine Power Systems, Vol. I, II, Bureau of Mines, 1981.

14. "Type Co (HiLo) Overcurrent Relay," Westinghouse I.L. 41-100B, 1976.

15. "Molded Case Circuit Breaker Ges G111B," General Electric.

APPENDIX A

CURVE-SMOOTHING PROGRAMS

```
C       TITLE:DIGIT.F4;CREATES FILES FROM DATA
         USING NUMONICS ARM
**********************************************************
1       TYPE 5
5       FORMAT(' INPUT DEVICE NR..')
        ACCEPT 8,IDEV
8       FORMAT(I)
        OPEN(UNIT=IDEV)
        TYPE 10
10      FORMAT(' INPUT X-AXIS DIMENSION,Y-AXIS
         DIMENSION'//'..,')
        ACCEPT 15,XAX,YAX
15      FORMAT(2F)
        TYPE 20
20      FORMAT(' INPUT LENGTH PER LOG10;X,Y..')
30      ACCEPT 35,XL,YL
35      FORMAT(2F)
        XAX=100*XAX/XL
        YAX=100*YAX/YL
        CALL OPEN(30,'DEVICE','NUM','MODE','IMAGE',
        1'ACCESS','SEQIN','BUFFERS',4)
        CALL NUMRES(30,4)
        CALL LOCK(1,1)
100     READ(30,END=200) IDATA
        IX=(IDATA/"1000000).AND."37777
        IY=IDATA.AND."37777
        IFLAGS=(IDATA.AND."740000)/"40000
        X=IX/XAX
        Y=IY/YAX
        WRITE(IDEV,150)IFLAGS,X,Y
150     FORMAT(I,2F)
        GO TO 100
200     CALL NUMCLO
        CALL UNLOCK(1,1)
        CLOSE(UNIT=IDEV)
        TYPE 210
210     FORMAT(' CONTINUE?..,'$)
        ACCEPT 220,IC
220     FORMAT(I)
        IF(IC.EQ.0)GO TO 1
        STOP
        END
```

```
*****************************************************
C       CURVE FITTING PROGRAM:DEV.F4
*****************************************************
        INTEGER L(7),MM(7)
        REAL X(100),YS(100)
        REAL*8 YM(100),G(7,7),U(7),A(0/6),GG(7,7),ERROR(100)
        TYPE 100
100     FORMAT(1X,'CHOOSE DIMENSION OF FIT  '$)
        ACCEPT 110,ND
110     FORMAT(I)
        TYPE 120
120     FORMAT(1X,'CHOOSE NO. OF POINTS   '$)
        ACCEPT 110,M
        TYPE 130
130     FORMAT(/'CHOOSE INPUT FILES'/' ...,   '$)
        ACCEPT 110,IUNIT1
        DO 140  I=1,M
        READ(IUNIT1,135)J,X(I),YS(I)
135     FORMAT(I,2F)
        YS(I)=ALOG10(YS(I))
140     CONTINUE
        DO 10 K=1,M
        DO 10 I=1,ND
        U(I)=U(I)+YS(K)*X(K)**(I-1)
        DO 10 J=1,ND
        G(I,J)=G(I,J)+X(K)**(I+J-2)
10      CONTINUE
        CALL DMINV(G,7,ND)
        DO 20 I=0,ND-1
        DO 20 J=1,ND
        A(I)=A(I)+G(I+1,J)*U(J)
20      CONTINUE
        DO 30 I=1,M
        DO 30 J=0,ND-1
        YM(I)=YM(I)+A(J)*X(I)**J
30      CONTINUE
        DO 40 I=1,M
40      SQUERR=SQUERR+(YS(I)-YM(I))**2
        TYPE 160,SQUERR
160     FORMAT(' THE INTERGRAL-SQUARED ERROR IS:   ',E)
        OPEN(UNIT=40,FILE='A.DAT')
        WRITE(40,170)A
        CLOSE(UNIT=40)
170     FORMAT(D)
        TYPE 99,IUNIT1
99      FORMAT(' IUNIT=',I)
        DO 50 I=1,M
50      ERROR(I)=DABS((YM(I)-YS(I))/YS(I))
        OPEN(UNIT=41,FILE='YINOUT.DAT')
        WRITE(41,180)(X(I),YS(I),YM(I),ERROR(I),I=1,M)
180     FORMAT(2F,2D)
```

```
      CLOSE(UNIT=41)
      STOP
      END
C     TITLE:DMINV;SUBROUTINE TO INVERT A REAL SQUARE
MATRIX DOUBLE
C     PRECISION
      SUBROUTINE DMINV(A,MDIM,N)
      REAL*8 A(MDIM,N)
      INTEGER L(100),M(100)
C
C     CONVERTED FROM SSP ROUTNE MINV
C
      DOUBLE PRECISION BIGA,HOLD
      DO 80 K=1,N
      L(K)=K
      M(K)=K
      BIGA=A(K,K)
      DO 20 J=K,N
      DO 20 I=K,N
10    IF(DABS(BIGA)-DABS(A(I,J))) 15,20,20
15    BIGA=A(I,J)
      L(K)=I
      M(K)=J
20    CONTINUE
      J=L(K)
      IF(J-K) 35,35,25
25    DO 30 I=1,N
      HOLD=-A(K,I)
      A(K,I)=A(J,I)
30    A(J,I)=HOLD
35    I=M(K)
      IF(I-K) 45,45,38
38    DO 40 J=1,N
      HOLD=-A(J,K)
      A(J,K)=A(J,I)
40    A(J,I)=HOLD
45    DO 55 I=1,N
      IF(I-K) 50,55,50
50    A(I,K)=A(I,K)/(-BIGA)
55    CONTINUE
      DO 65 I=1,N
      HOLD=A(I,K)
      DO 65 J=1,N
      IF(I-K) 60,65,60
60    IF(J-K) 62,65,62
62    A(I,J)=HOLD*A(K,J)+A(I,J)
65    CONTINUE
      DO 75 J=1,N
      IF(J-K) 70,75,70
70    A(K,J)=A(K,J)/BIGA
75    CONTINUE
```

```
      A(K,K)=(1.0000000)/BIGA
80    CONTINUE
      K=N
100   K=K-1
      IF(K) 150,150,105
105   I=L(K)
      IF(I-K) 120,120,108
108   DO 110 J=1,N
      HOLD=A(J,K)
      A(J,K)=-A(J,I)
110   A(J,I)=HOLD
120   J=M(K)
      IF(J-K) 100,100,125
125   DO 130 I=1,N
      HOLD=A(K,I)
      A(K,I)=-A(J,I)
130   A(J,I)=HOLD
      GO TO 100
150   RETURN
      END
```

AD-A134 053 A COMPUTATIONAL PROCEDURE FOR THE PROTECTION OF 2/2
INDUSTRIAL POWER SYSTEMS(U) EENNSYLVANIA STATE UNIV
UNIVERSITY PARK DEPT OF ELECTRICAL ENGINEERING
UNCLASSIFIED C N SALMOND NOV 81 F/G 10/2 NL





MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963-A

APPENDIX B

COORDINATION AND PLOTTING PROGRAMS

```
**********************************************************
C       INPUT.IT INPUTS DATA FROM A TERMINAL,PLACES IN
C       THE PROPER FORMAT FOR OTHER PROGRAMS
**********************************************************
C
C
        DIMENSION
L(30,30,2),PU(30,30,1),RES(30,30,2),E(30),XL(30,30,2)
        DIMENSION
S(300),ZER(30,30,2),RC(7),XC(7),ZG(30),XD(30)
        COMPLEX T1,TPU,PU,S,S1,PU1,PZ,CUR,ZER,ZG
        REAL*8 A(7),AA(7)
        REAL L
**************************************************************
C       IF THE PROGRAM HAS ALREADY BEEN RUN ONCE ALL DATA
C       NEED NOT BE ENTERED AGAIN
**************************************************************
        TYPE 3
3       FORMAT(' DO YOU WANT TO READ DATA FROM A FILE OR
FROM KYBRD?'/
        2' <CR>FOR INPUT FROM TTY,1 FOR READ...')
        ACCEPT 11,I
        IF(I.NE.0)GO TO 400
**************************************************************
C       INPUT OF DATA ON LINES
**********************************************************
        TYPE 5
5       FORMAT(2X,'ENTER THE PROBLEM BASE IN MVA')
        ACCEPT 10,ZBASE
        TYPE 6
6       FORMAT(2X,'ENTER THE PROBLEM BASE IN KV')
        ACCEPT 10,EBASE
10      FORMAT(F)
11      FORMAT(I)
        GO TO 14
**********************************************************
C       PROGRAM RETURNS HERE AFTER READING DATA AT 400
**********************************************************
12      TYPE 13
13      FORMAT(' OLD DATA IS ENTERED,READY FOR NEW LINE
DATA..')
        ACCEPT 11,I
14      TYPE 15
15      FORMAT(/,2X,'ENTER ELEMENT DATA AS
FOLLOWS:BUS()TO()(LENGTH)
        1(SP)SIZE',/,2X,'(TRANSFORMER
IMPEDENCE(P.U.))(TRANSFORMER SIZE
        2IN MVA) SP',/, 2X,'(TRANSFORMER HIGH VOLTAGE IN KV)
SP',/,'
        3(TRANSFORMER LOW VOLTAGE IN KV]...,'/)
**********************************************************
```

```
C       THESE TWO FILES CONTAIN COEFFICIENT DATA FO 40 BELOW
C       THEY ARE CREATED USING THE CURVE FITTING
PROGRAM:CURV.F4
*************************************************************
        OPEN(UNIT=40,FILE='RES.DAT')
        OPEN(UNIT=35,FILE='XFOR.DAT')
        READ(40,20)(A(I),I=1,7)
        READ(40,20)(AA(I),I=1,7)
20      FORMAT(D)
        DO 21 I=1,7
        RC(I)=A(I)
        XC(I)=AA(I)
21      CONTINUE
        CLOSE(UNIT=40)
        CLOSE(UNIT=41)
22      ACCEPT 24,I,J,XLL,WIR,II,PSI,TVH,TVL
24      FORMAT(2I,7F)
        IF(I.EQ.0) GO TO 110
        TYPE 26
        JJ=1
26      FORMAT('  PARALLEL LINE   1 TO 3...,',$)
        ACCEPT 27,JJ
27      FORMAT(I)
        IF(JJ.EQ.0)JJ=1
        L(I,J,JJ)=XLL
        IF(WIR.EQ.140)GO TO 31
        IF(WIR.EQ.130)GO TO 32
        IF(WIR.EQ.120)GO TO 33
        IF(WIR.EQ.110)GO TO 34
        SA=WIR
        SB=WIR
        IF(SA.LT.37)GO TO 35
        GO TO 40
31      SA=-3
        GO TO 35
32      SA=-2
        GO TO 35
33      SA=-1
        GO TO 35
34      SA=0
        GO TO 35
*************************************************************
C       CONVERSION FROM AWG TO MCM
*************************************************************
35      SC=1.1229**(36-SA)
        SD=.005*SC
        SE=SD**2
        SB=1000*SE
*************************************************************
C       FORMULAE FOR LINE RESISTANCE AND REACTANCE
*************************************************************
```

```
40
RES(I,J,JJ)=RC(1)+RC(2)*(ALOG10(SB))+RC(3)*(ALOG10(SB
)**2)+

1RC(4)*(ALOG10(SB)**3)+RC(5)*(ALOG10(SB)**4)+RC(6)*(A
LOG10(SB)
        2**5)+RC(7)*(ALOG10(SB)**6)

XL(I,J,JJ)=XC(1)+XC(2)*(ALOG10(SB))+XC(3)*(ALOG10(SB)
**2)+

1XC(4)*(ALOG10(SB)**3)+XC(5)*(ALOG10(SB)**4)+RC(6)*(A
LOG10(SB)
        2**5)+XC(7)*(ALOG10(SB)**6)
        TYPE 50,RES(I,J,JJ),SA,SB,XL(I,J,JJ)
50      FORMAT(2X,'LINE RES. ',3F,/,'LINE REACT..',F)
        IF(CABS(T1).EQ.0)GO TO 85
        PU(I,J,JJ)=T1*(ZBASE/TS1)*((TVH/EBASE)**2)
        TYPE 55,I,J
55      FORMAT(' INPUT TRANSFORMER ZN IN P.U. REFER TO BUS
SIDE,(BUS
        1',I3,')SP(BUS ',I3,')..,')
        ACCEPT 60,S1,PU1
60      FORMAT(4F)
        TV=TVH*1E3
        ZG(I)=S1*(ZBASE/TS1)*((EBASE/TVH)**2)
        ZG(J)=PU1*(ZBASE/TS1)*((EBASE/TVL)**2)
        CURB=TS1*1E6/TV
        TINRSH=12*CURB
        TWST1=25*CURB
        TWST2=14.4*CURB
        WRITE(35,70)I,J,TINRSH,TWST1,TWST2,TS1
70      FORMAT(2I,4F)
85      IF(IMAX.GT.I) GO TO 90
        IMAX=I
90      IF(JMAX.GT.J) GO TO 100
        JMAX=J
100     ZER(I,J,JJ)=CMPLX(0.0,XL(I,J,JJ))
        TYPE 102,ZER(I,J,JJ),SS1
102     FORMAT(3F)
        GO TO 22
110     OPEN(UNIT=31,FILE='RELA.DAT')
        OPEN(UNIT=32,FILE='TEST.DAT')
        OPEN(UNIT=33,FILE='LOCUR.DAT')
        IF(IMAX.LT.JMAX) GO TO 115
        IB=IMAX
        GO TO 118
115     IB=JMAX
*****************************************************************
C       BUS VOLTAGES ARE INPUT
*****************************************************************
```

```
118     DO 120 I=1,IB
        TYPE 119,I
119     FORMAT(' INPUT BUS',I3,'VOLTAGE...,',$)
        ACCEPT 10,E2
        IF(E2.EQ.0)GO TO 121
        E(I)=E2
120     CONTINUE
121     TYPE 122
122     FORMAT(/,2X,'DATA IS ACCEPTED AND A LIST FOLLOWS')
        TYPE 125,ZBASE
125     FORMAT(2X,'PROBLEM BASE IN MVA..,',F)
        WRITE(31,126)ZBASE,EBASE,IB
126     FORMAT(2F,I)
        E1=E(1)/(EBASE*1E3)
        WRITE(32,128),IB,E1
128     FORMAT(I,2F)
        DO 135 I=1,30
        DO 133 J=1,30
        DO 133 JJ=1,2
        IF(L(I,J,JJ).EQ.0)GO TO 133
        NN=NN+1
        PZ=(CMPLX(RES(I,J,JJ),XL(I,J,JJ)))*(.001*L(I,J,JJ))
        PZZ=(ZBASE*1E6)/(E(I)**2)
        PZ=PZ*PZZ
        T1=PZ+PU(I,J,JJ)
        ZER(I,J,JJ)=ZER(I,J,JJ)*PZZ*(.001*L(I,J,JJ))+T1
        TYPE 130,NN,L(I,J,JJ),T1
130     FORMAT(2X,'ELEMENT  ',I3,5X,'LENGTH',F,/,
        11X,'TRANSFORMERPER UNIT IMPEDENCE PLUS LINE
IMPEDENCE',2F)

WRITE(31,131)I,J,JJ,L(I,J,JJ),RES(I,J,JJ),PU(I,J,JJ),
XL(I,J,JJ)
        1,ZG(I),ZG(J)
131     FORMAT(3I,9F)
        WRITE(32,132)NN,I,J,JJ,T1,ZER(I,J,JJ),ZG(I),ZG(J)
132     FORMAT(4I,8F)
133     CONTINUE
135     CONTINUE
        WRITE(31,136)
        WRITE(32,136)
136     FORMAT('  0 0 0 0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0')
        DO 138 I=1,IB
        WRITE(31,137)I,E(I)
137     FORMAT(I,2F)
138     CONTINUE
        WRITE(31,139)
139     FORMAT(' 0 0.0 0.0')
        TYPE 140,IB
140     FORMAT(10X,'NUMBER OF BUSSES IS...,',I)
145     TYPE 150
```

```
**************************************************************
150     FORMAT(//' NOW ENTER THE LOAD DATA IN THE FOLLOWING
MANNER;...
        1'/'(BUS  )(LOAD IN KVA)(PWR FACTOR)...OR...
        2'/' (BUS ) (LOAD IN HP)(PWR FACTOR)....OR....'/
        3'(BUS )(LOAD IN AMPS)(PWR FACTOR)')
        DO 300 N=1,IB
               TYPE 160
160            FORMAT(' WHAT METHOD WILL YOU USE
?..VA,HP,OR AMPS??')
               ACCEPT 162,MD
162            FORMAT(A4)
               TYPE 164,MD
164            FORMAT(2X,A4,' ENTER...')
               IF(MD.EQ.'HP1') GO TO 170
               IF(MD.EQ.'HP') GO TO 170
               IF(MD.EQ.'AMPS') GO TO 180
               IF(MD.EQ.'S') GO TO 305
               MD='VA'
               ACCEPT 165, J,AS1,PFAC
165            FORMAT(I,2F)
               SZTZ=AS1/(ZBASE*1E3)
               SZR=SZTZ*PFAC
               PCOS=ACOS(PFAC)
               SZI=SZTZ*SIN(PCOS)
               S(J)=CMPLX(SZR,SZI)
               AI=AS1*1E3/(E(J)*SQRT(3.0))
               WRITE(33,168)J,AI
168            FORMAT(I,F)
               ST=MD
               GO TO 300
170            ACCEPT 175,I,PRH,PFAC
175            FORMAT(I,3F)
               SZTZ=PRH*7.46
               SZR=SZTZ*PFAC
               PCOS=ACOS(PFAC)
               SZI=SZTZ*SIN(PCOS)
               S(I)=CMPLX(SZR,SZI)/(ZBASE*1E6)
               IF(MD.EQ.'HP')XD(I)=.17/CABS(S(I))
               AI=SZTZ/(SQRT(3.0)*E(I))
               WRITE(33,178)I,AI
178            FORMAT(I,F)
               ST=MD
               GO TO 300
180            ACCEPT 185,I,CURT,PFAC
185            FORMAT(I,3F)
               WRITE(33,187)I,CURT
187            FORMAT(I,F)
               CURR=CURT*PFAC
               PCOS=ACOS(PFAC)
               CURI=CURT*SIN(PCOS)
```

```
                CUR=CMPLX(CURR,CURI)
                CUR=CUR*(SQRT(3.0)*EBASE/ZBASE)
                S(I)=3*EBASE*CONJG(CUR)/SQRT(3.0)
                ST=MD
300         CONTINUE
305         DO 320 N=1,IB
                NN=N
                TYPE 310,N,S(N),MD
310         FORMAT(' BUS ',I3,2F,A4,2F)
                WRITE(31,312)NN,S(NN)
312         FORMAT(I,2F)
                WRITE(32,315)N,S(N),XD(NN)
315         FORMAT(I,3F)
320         CONTINUE
            WRITE(31,330)
            WRITE(32,331)
330         FORMAT('  0 0.0 0.0')
331         FORMAT('  0 0.0 0.0')
            WRITE(33,332)
332         FORMAT(' 0 0.0')
            WRITE(35,335)
335         FORMAT(' 0 0 0.0 0.0 0.0 0.0 ')
            GO TO 900
400         OPEN(UNIT=36,FILE='RELA.DAT')
            READ(36,411) ZBASE,EBASE,IB
            IMAX=IB
411         FORMAT(2F,I)
450         READ(36,456)I,J,JJ,XL3,RES1,PU1,XL2,T1,S1
456         FORMAT(3I,9F)
            IF(I.EQ.0)GO TO 470
            L(I,J,JJ)=XL3
            RES(I,J,JJ)=RES1
            PU(I,J,1)=PU1
            XL(I,J,JJ)=XL2
            ZER(I,J,JJ)=CMPLX(0.0,XL2)
            ZG(I)=T1
            ZG(J)=S1
            IF(I.NE.0)GO TO 450
470         READ(36,472)I,E(I)
472         FORMAT(I,2F)
            IF(I.NE.0) GO TO 470
457         READ(36,458)I,S1
458         FORMAT(I,2F)
            S(I)=S1
            IF(I.NE.0) GO TO 457
            REWIND 36
            JJ=0
            CLOSE(UNIT=36)
            GO TO 12
900         CLOSE(UNIT=31)
            CLOSE(UNIT=32)
```

```
      CLOSE(UNIT=35)
      STOP
      END
*****************************************************************
C     LDFLO.F4:A LOAD FLOW PROGRAM
*****************************************************************
      DIMENSION
E(33),Y1(33,33),PSCH(33),QSCH(33),PCAL(33),

1QCAL(33),PDIFF(33),QDIFF(33),IC(33),S(33),JAC(68,68)
,
      2PQVEC(33),EFDV(64),QQVEC(33),
      3YS(33,33),Y(33,33),CRFLO(33,33),U(68),V(68),
      4EDIFF(33)
      INTEGER P,Q,M,U,V,PP
      COMPLEX E,IC,Y,Z,YS,Y1,PFLO,PLOS,YSH,EDIFF,
      1S,CRFLO,PFLO1,ZG1,ZNI,ZNJ
      EQUIVALENCE (CRFLO,Y1)
      REAL JAC
      DIMENSION EIDV(64)

OPEN(UNIT=30,DEVICE='DSK',FILE='TEST.DAT',DISPOSE='SA
VE')
      OPEN(UNIT=33,DEVICE='DSK',FILE='DSK.XFR')
*****************************************************************
CREAD VALUES OF IMPEDANCES  YSHUNT ADMITTANCES

C     888888*****IF SHUNT ADMITTANCES ARENOT IGNORED
REMOVE
***THE C IN THE LINE YS(Q,P)*****************************
C*****************************************************
      READ(30,2) IB,E1
2     FORMAT(I,F)
      E(1)=CMPLX(E1,0.0)
      DO 10 I=1,1000
      READ(30,5)NN,P,Q,JJ,Z,ZG1,ZNI,ZNJ
5     FORMAT(4I,8F)
      IF(P.EQ.0) GO TO 15
      YS(P,Q)=YSH
C     YS(Q,P)=YSH
      IF(CABS(Y1(P,Q)).NE.0)Z=1.0/(Y1(P,Q)+1/Z)
      Y1(P,Q)=1.0/Z
      Y1(Q,P)=Y1(P,Q)
      PRINT 6,P,Q,Y1(P,Q),YS(P,Q)
6     FORMAT(2I,4F)
10    CONTINUE
*****************************************************************
CCOMPILE TERMS FOR YBUS
C*************************************************
15    DO 50 P=1,IB
      Y(P,P)=0
```

```
        DO 40 Q=1,IB
        IF(P.EQ.Q) GO TO 40
        Y(P,P)=Y(P,P)+Y1(P,Q)+YS(P,Q)
        Y(P,Q)=-Y1(P,Q)
40      CONTINUE
50      CONTINUE
C*************************************************
C PRINT OUT VALUES OF YBUS
C*************************************************
        PRINT 51
51      FORMAT ('0',10X,'BUS IMPEDANCE MATRIX,YBUS')
        DO 58 I=1,IB
        PRINT 54,(Y(I,J),J=1,IB)
54      FORMAT('0',100F)
58      CONTINUE
C*************************************************
C READ VALUES OF POWER AT BUSSES
C*************************************************
        DO 60 P=1,IB
        READ(30,59) I,PS,QS
        IF(I.EQ.0)GO TO 62
        IF(I.EQ.1)GO TO 60
        PSCH(I)=-PS
        QSCH(I)=-QS
59      FORMAT(I,2F)
60      CONTINUE
C*************************************************
C ASSUME VALUES OF VOLTAGE AT BUSSES
C*************************************************
62      DO 70 P=2,IB
        E(P)=(1.0,0.0)
70      CONTINUE
        K=0
        DO 80 I=1,IB
                TYPE 75,I,E(I)
75      FORMAT(I,2F)
80      CONTINUE
122     PRINT 123,K
123     FORMAT ('0',85X,'ITERATION = ',I2)
C*************************************************
C CALCULATES REAL  REACTIVE BUSS POWERS
C*************************************************
        DO 150 P=2,IB
        PSUM=0
        QSUM=0
        DO 140 Q=1,IB

P1=REAL(E(P))*(REAL(E(Q))*REAL(Y(P,Q))-AIMAG(E(Q))*AI
MAG(Y

1(P,Q)))+AIMAG(E(P))*(AIMAG(E(Q))*REAL(Y(P,Q))+RCAL(E
```

```
(Q))*
     2AIMAG(Y(P,Q)))

Q1=AIMAG(E(P))*(REAL(E(Q))*REAL(Y(P,Q))-AIMAG(E(Q))*A
IMAG(Y

1(P,Q)))-REAL(E(P))*(AIMAG(E(Q))*REAL(Y(P,Q))+REAL(E(
Q))*AI
     2MAG(Y(P,Q)))
     PSUM=PSUM+P1
     QSUM=QSUM+Q1
140  CONTINUE
     PCAL(P)=PSUM
     QCAL(P)=QSUM
     PRINT 145,PCAL(P),QCAL(P)
145  FORMAT(2F)
150  CONTINUE
C*****************************************************
C PRINT OUT VALUES OF CALCULATED BUSS POWERS
C*****************************************************
     PRINT 155,K
155  FORMAT('0','REAL AND REACTIVE BUSS POWERS K=',I2)
     DO 158 I=2,IB
     PRINT 157,PCAL(I),QCAL(I)
157  FORMAT ('0',2F)
158  CONTINUE
     M=0
     DO 160 P=2,IB
     EP=0.01
     PDIFF(P)=PSCH(P)-PCAL(P)
     QDIFF(P)=QSCH(P)-QCAL(P)
     TDIFF=ABS(PDIFF(P))+ABS(QDIFF(P))
     IF(TDIFF.LT.EP) GO TO 160
     M=1
160  CONTINUE
C*************************************************
C PRINT OUT VALUES OF DIFFERENTIAL BUSS POWERS
C*************************************************
     PRINT 165,K
165  FORMAT('0','DIFFERENTIAL PQ   K=',3X,I2)

     DO 168 I=2,IB
     PRINT 167,PDIFF(I),QDIFF(I)
167  FORMAT ('0',2F)
168  CONTINUE
     IF(M.EQ.0) GO TO 400
     DO 170 I=2,IB
     S(I)=CMPLX(PCAL(I),QCAL(I))
170  CONTINUE
C*********************************************
C  CALCULATE BUSS CURRENTS I(P) EXCEPT AT SLACK BUS
```

```
C*********************************************
        DO 175 I=2,IB
        IC(I)=CONJG(S(I))/CONJG(E(I))
        PRINT 173,IC(I)
173     FORMAT(F)
175     CONTINUE
C*********************************************
C  CALCULATE JACOBIAN USING PARTITIONS 'J1,J2,J3,J4'
C*********************************************
C  JACOBIAN 'J1'
C***************
        IBDJ=2*IB-2
        IBJ=IB-1
        DO 190 M=1,IBJ
        DO 180 N=1,IBJ
        P=M+1
        Q=N+1

JAC(M,N)=(REAL(E(P))*REAL(Y(P,Q)))+(AIMAG(E(P))*AIMAG
(Y(P,Q)))
        IF(P.NE.Q) GO TO 177
        JAC(M,N)=JAC(M,N)+REAL(IC(P))
177     CONTINUE
C       PRINT 178,JAC(M,N),E(P),Y(P,Q)
178     FORMAT(5F)
180     CONTINUE
190     CONTINUE
*****************************************************************
C  JACOBIAN 'J2'
*****************************************************************
        DO 210 M=1,IBJ
        DO 200 N=IB,IBDJ
        P=M+1
        Q=N-IB+2

JAC(M,N)=-REAL(E(P))*AIMAG(Y(P,Q))+AIMAG(E(P))*REAL(Y
(P,Q))
        IF(P.NE.Q) GO TO 195
        JAC(M,N)=JAC(M,N)+AIMAG(IC(P))
195     CONTINUE
200     CONTINUE
210     CONTINUE
*****************************************************************
C  JACOBIAN 'J3'
*****************************************************************
        DO 230 M=IB,IBDJ
        DO 220 N=1,IBJ
        P=M-IB+2
        Q=N+1

JAC(M,N)=-REAL(E(P))*AIMAG(Y(P,Q))+AIMAG(E(P))*REAL(Y
```

```
(P,Q))
          IF(P.NE.Q) GO TO 215
          JAC(M,N)=JAC(M,N)-AIMAG(IC(P))
215       CONTINUE
220       CONTINUE
230       CONTINUE
**********************************************************
C  JACOBIAN 'J4'
**********************************************************
          DO 250 M=IB,IBDJ
          DO 240 N=IB,IBDJ
          P=M-IB+2
          Q=N-IB+2

JAC(M,N)=-AIMAG(E(P))*AIMAG(Y(P,Q))-REAL(E(P))*REAL(Y
(P,Q))
          IF(P.NE.Q) GO TO 235
          JAC(M,N)=JAC(M,N)+REAL(IC(P))
235       CONTINUE
240       CONTINUE
250       CONTINUE
          DO 334 M=1,IBDJ
C         PRINT 333,(JAC(M,N),N=1,IBDJ)
333.      FORMAT(18F)
334       CONTINUE
**********************************************************************
**********************************************************************
C  COMPUTE INVERSE OF JACOBIAN
          CALL MINV(JAC,68,IBDJ)
**********************************************************
C         PRINT 344,(JAC(M,N),N=1,IBDJ)
344       FORMAT(18F)
345       CONTINUE
**********************************************************
C  COMPUTE DIFERENCE IN VOLTAGE USING JACOBIAN INVERSE 'JAC'
**********************************************************
          DO 346 I=2,IB
          M=I-1
          PQVEC(M)=PDIFF(I)
          QQVEC(M)=QDIFF(I)
346       CONTINUE
          J=IB-1
          DO 351 M=1,J
          EFDVD=0
          EFDQD=0
          EIDD=0
          EIQV=0
          DO 349 N=1,J
          EFDVD=EFDVD+JAC(M,N)*PQVEC(N)
349       CONTINUE
          DO 350  N=IB,IBDJ
```

```
          NQ=N-J
          EFDQD=EFDQD+JAC(M,N)*QQVEC(NQ)
350       CONTINUE
          EFDV(M)=EFDQD+EFDVD
351       CONTINUE
          DO 360 M=IB,IBDJ
          EIDD=0
          EIQV=0
          DO 358 N=1,J
          EIDD=EIDD+JAC(M,N)*PQVEC(N)
358       CONTINUE
          DO 359 N=IB,IBDJ
          NQ=N-J
          EIQV=EIQV+JAC(M,N)*QQVEC(NQ)
359       CONTINUE
          EIDV(M)=EIQV+EIDD
360       CONTINUE
**************************************************************
C  COMPUTE NEW BUS VOLTAGES USING 'EFDV' EFDIFFERENTIAL
VECTOR
**************************************************************
          DO 370 P=2,IB
          M=P-1
          N=M+J
          IBZ=2*(IB-1)
          IF(N.GT.IBZ) GO TO 370
          EDIFF(P)=CMPLX(EFDV(M),EIDV(N))
          PRINT 368,P,EDIFF(P)
368       FORMAT(I,2F)
          E(P)=E(P)+EDIFF(P)
370       CONTINUE
          IF(K.EQ.10)GO TO 390
          K=K+1
          GO TO 122
390       TYPE 395
395       FORMAT(' AN ERROR IS MADE IN DATA, LOAD FLOW DID NOT
CONVERGE')
400       CONTINUE
500       CLOSE(UNIT=30)
**************************************************************
C         COMPUTE POWER FLOWS BUS P TO Q
C         COMPUTE CURRENT FLOWS AND POWER LOSSES
C         COMPUTE SLACK BUS POWER
**************************************************************
          OPEN(UNIT=31,FILE='DSK')
          S(1)=0
503       FORMAT(I)
          DO 520 P=1,IB
          DO 515 Q=1,IB
          IF(P.EQ.Q) GO TO 515
          IF(Y(P,Q).EQ.(0.0,0.0)) GO TO 515
```

```
          PP=P
**********************************************************
C         IF YOU ARE NOT NEGLECT SHUNT ADMITT REMOVE THE NEXT
C
**************************************************************
          PFLO=CONJG(E(P))*((E(P)-E(Q))*Y1(P,Q))
C         1+(CONJG(E(P))*E(P)*YS(P,Q))
          PFLO1=CONJG(E(Q))*((E(Q)-E(P))*Y1(P,Q))
C         1+(CONJG(E(Q))*E(Q)*YS(P,Q))
          CRFLO(P,Q)=PFLO/CONJG(E(P))
          PLOS=PFLO+PFLO1
**************************************************************
C         TAKE THE CONJUGATE OF THE POWER FLOWS FOR FORMAT
P-JQ
**************************************************************
          PLOS=CONJG(PLOS)
          PFLO=CONJG(PFLO)
          IF(P.NE.1) GO TO 505
          S(1)=PFLO+S(1)
505       WRITE(31,509)P,Q,PFLO,CRFLO(P,Q),PLOS
          WRITE(31,510)PP,E(PP)
509       FORMAT(6X,'POWER FLOW
BUS',I2,'TO',I2,'IS',2F,2X,'CURRENT
          1FLOW IS',2F,'POWER LOSS IS',2F)
510       FORMAT(5X,'BUS',I2,'VOLTAGE IS',2F)
515       CONTINUE
520       CONTINUE
          WRITE(31,540) S(1)
540       FORMAT(6X,'POWER AT SLACK BUS 1 IS',2F)
          DO 550 M=1,IB
                    DO 545 N=1,IB
                    IF(CABS(CRFLO(M,N)).GT.0.000001)
WRITE(33,543)M,N,
          1CRFLO(M,N)
543       FORMAT(2I,2F)
545                 CONTINUE
550       CONTINUE
          WRITE(33,555)
555       FORMAT(' 0   0   0.0 0.0')
          CLOSE(UNIT=33)
          DO 600 M=1,IB
          DO 580 N=1,IB
          S(2)=E(M)*CONJG(CRFLO(M,N))
          PFAD=CABS(S(2))
          IF(PFAD.EQ.0) GO TO 580
          PFAC=-(REAL(S(2)))/(PFAD)
          WRITE(31,570)M,N,PFAC
570       FORMAT(4X,'POWER FACTOR BUS',I3,'TO',I3,'IS',F)
580       CONTINUE
600       CONTINUE
          CLOSE(UNIT=31)
```

```
      STOP
      END
C     TITLE:MINV;SUBROUTINE TO INVERT A REAL SQUARE MATRIX
      SUBROUTINE MINV(A,MDIM,N)
      DIMENSION A(MDIM,N)
      INTEGER L(100),M(100)
C
C     CONVERTED FROM SSP ROUTNE MINV
C
      DO 80 K=1,N
      L(K)=K
      M(K)=K
      BIGA=A(K,K)
      DO 20 J=K,N
      DO 20 I=K,N
10    IF(ABS(BIGA)-ABS(A(I,J))) 15,20,20
15    BIGA=A(I,J)
      L(K)=I
      M(K)=J
20    CONTINUE
      J=L(K)
      IF(J-K) 35,35,25
25    DO 30 I=1,N
      HOLD=-A(K,I)
      A(K,I)=A(J,I)
30    A(J,I)=HOLD
35    I=M(K)
      IF(I-K) 45,45,38
38    DO 40 J=1,N
      HOLD=-A(J,K)
      A(J,K)=A(J,I)
40    A(J,I)=HOLD
45    DO 55 I=1,N
      IF(I-K) 50,55,50
50    A(I,K)=A(I,K)/(-BIGA)
55    CONTINUE
      DO 65 I=1,N
      HOLD=A(I,K)
      DO 65 J=1,N
      IF(I-K) 60,65,60
60    IF(J-K) 62,65,62
62    A(I,J)=HOLD*A(K,J)+A(I,J)
65    CONTINUE
      DO 75 J=1,N
      IF(J-K) 70,75,70
70    A(K,J)=A(K,J)/BIGA
75    CONTINUE
      A(K,K)=(1.0000000)/BIGA
80    CONTINUE
      K=N
100   K=K-1
```

```
      IF(K) 150,150,105
105   I=L(K)
      IF(I-K) 120,120,108
108   DO 110 J=1,N
      HOLD=A(J,K)
      A(J,K)=-A(J,I)
110   A(J,I)=HOLD
120   J=M(K)
      IF(J-K) 100,100,125
125   DO 130 I=1,N
      HOLD=A(K,I)
      A(K,I)=-A(J,I)
130   A(J,I)=HOLD
      GO TO 100
150   RETURN
      END
*************************************************************
C     TITLE:ZBUS.F4;ACCEPTS DATA FROM TEST.DAT AND DSK.XFR
FROM
C           LOAD FLOW PROGRAM LDFLO.F4 AND FORMS ZBUS BY
C           ALGORITHM THIS WILL BE USED TO COMPUTE ALL
FAULT
C           CURRENTS.LOAD FLOW COMPUTED MAXIMUM LOAD
CURRENTS.
*************************************************************
*************************************************************
C     READ DATA FROM TEST.DAT
*************************************************************
      DIMENSION
ZD(300,3),ZM(300,2),RID(30,30,3),ZG(30),ZN(30),

1ID(200),RI(30),ZB(30,30),ZBO(30,30),ZMU(5,5),IDD(5),
ZL(30),
      2ZBR(30),ZGO(30),ZLO(30),EB(30)
      COMPLEX ZD,ZM,ZG,T1,ZN,ZN1,ZNI,ZNJ,ZG1,ZO,
      1ZB,ZBO,ZMU,ZBB,ZL,ZLL,ZBR,ZGO,ZLO,ZLLO,EB
      NNB=1
      EQUIVALENCE(ZBR,ZLO,EB)
      OPEN(UNIT=31,FILE='TEST.DAT')
C     OPEN(UNIT=32,FILE='DSK.XFR')
      READ(31,10)IB,EB1
10    FORMAT(I,F)
20    READ(31,30)NB,I,J,JJ,T1,ZG1,ZNI,ZNJ
30    FORMAT(4I,8F)
      IF(NB.EQ.0) GO TO 40
      DN=NB
      NN=NB
      ZD(NN,1)=CMPLX(DN,0.0)
      ZD(NN,2)=T1
      ZD(NN,3)=ZG1+3*ZN(I)
      ZN(I)=ZNI
```

```
          ZN(J)=ZNJ
          RID(I,J,JJ)=NN
          IF(NB.NE.0)GO TO 20
40        DO 45 I=1,IB
C         READ(32,43)T1
43        FORMAT(2F)
45        CONTINUE
          DO 48 I=1,IB
C         READ(32,46)J,T1
46        FORMAT(I,2F)
          EB(J)=T1
48        CONTINUE
49        READ(31,50)I,T1,XD1
50        FORMAT(I,3F)
          IF(I.EQ.0) GO TO 60
          IF(CABS(T1).EQ.0) GO TO 49
C         T1=CONJG(T1)
C         ZG(I)=3*(CABS(EB(I))**2)/T1
          IF(XD1.NE.0)ZG(I)=CMPLX(0.0,XD1)
          ZGO(I)=ZG(I)
          IF(I.NE.0) GO TO 49
**********************************************************
C         ENTER THE ZERO SEQ IMP BUS   TO REF(GROUND)
**********************************************************
60        TYPE 62
62        FORMAT(' ENTER THE SYNC  ZERO SEQUENCE IMPEDENCE FOR
THE LOADS
          1AT EACH'/' BUS,3*ZN,MUST BE ADDED,IMPED IN PU..,')
          DO 65 I=1,IB
          ACCEPT 64,II,T1
          IF(II.EQ.0)GO TO 66
          ZGO(II)=T1
64        FORMAT(I,2F)
65        CONTINUE
66        DO 68 I=1,IB
          IF(CABS(ZGO(I)).EQ.0)ZGO(I)=ZG(I)
68        CONTINUE
**********************************************************
C         ENTER THE MUTUALLY COUPLED ELEMENTS
**********************************************************
          CLOSE(UNIT=31)
          TYPE 70
70        FORMAT(' ENTER THE MUTUALLY COUPLED ELEMENTS IN PER
UNIT'/'
          1 IN THE FOLLOWING FORMAT,TEST.DAT HAS THE ELEMENT
 S..,'/'
          2 (ELEMENT )SP TO(ELEMENT )SP(0 SEQ VALUE) ')
75        ACCEPT 80,EL,ELL,ZO
80        FORMAT(4F)
          IF(EL.EQ.0.0) GO TO 100
          II=II+1
```

```
      ZM(II,1)=CMPLX(EL,ELL)
      ZM(II,2)=ZO
      GO TO 75
*************************************************************
C     ALL ELEMENT DATA PREPARED PERFORM POSITIVE AND
NEGATIVE
C     SEQUENCE COMPUTATIONS TO FORM ZBUS
*************************************************************
*************************************************************
100   DO 500 IEL=1,NN
            BRA=0
            ID(IEL)=1
            DO 120 I=1,30
                  DO 120 J=1,30
                        DO 120 JJ=1,3
                        IF(RID(I,J,JJ).NE.IEL) GO TO
120
                              IF(RI(I).EQ.0)GO TO
110
                              IF(RI(J).EQ.0)GO TO
115
                              BRA=1.0
                              IPP=MINO(I,J)
                              IQQ=MAXO(I,J)
                              GO TO 130
110                           IF(RI(J).EQ.0)GO TO
115
                              RI(I)=1.0
                              IPP=J
                              IQQ=I
                              GO TO 130
115                           RI(J)=1.0
                              RI(I)=1.0
                              IPP=MINO(I,J)
                              IQQ=MAXO(I,J)
                              GO TO 130
120         CONTINUE
*************************************************************
C     BRANCH OR LINK HAS BEEN DETERMINED BRA=0:BRANCH
*************************************************************
130         DO 195 IL=1,IB
                  ZBB=CMPLX(0.0,0.0)
181               IF(BRA.NE.0) GO TO 186
                  IF(IQQ.EQ.IL) GO TO 190
                  ZBR(IL)=ZB(IPP,IL)
                  GO TO 190
186               ZL(IL)=ZB(IPP,IL)-ZB(IQQ,IL)
190               CONTINUE
195         CONTINUE
            ZBB=CMPLX(0.0,0.0)
            IF(BRA.NE.0) GO TO 250
```

```
                DO 200 IL=1,IB
                        ZB(IQQ,IL)=ZBR(IL)
                        ZB(IL,IQQ)=ZBR(IL)
200             CONTINUE
240             ZB(IQQ,IQQ)=ZB(IPP,IQQ)+ZD(IEL,2)
                ZBB=CMPLX(0.0,0.0)
                GO TO 300
250             ZLL=ZL(IPP)-ZL(IQQ)+ZD(IEL,2)
                ZBB=CMPLX(0.0,0.0)
                DO 290 IP=1,IB
                DO 290 IQ=1,IB
                                IF(IP.GT.IQ)GO TO 290

ZB(IP,IQ)=ZB(IP,IQ)-(ZL(IP)*Z
L(IQ)
        1/ZLL)
                                IF(IP.EQ.IQ) GO TO 290
                                ZB(IQ,IP)=ZB(IP,IQ)
290     CONTINUE
300             DO 350 I=1,5
                DO 350 J=1,5
                        ZMU(I,J)=CMPLX(0.0,0.0)
                        IDD(I)=0
350             CONTINUE
                DO 400 I=1,IB
                DO 400 J=1,IB
                        PRINT 380,I,J,ZB(I,J)
380                     FORMAT(2I,2F)
400             CONTINUE
                NNB=1
500     CONTINUE
*********************************************************
C               ZBUS POS/NEG IS FORMED
*********************************************************
        DO 505 I=1,NN
                ID(I)=0
505     CONTINUE
        DO 510 I=1,IB
                RI(I)=0.0
510     CONTINUE
        DO 1000 IEL=1,NN
                BRA=0
                ID(IEL)=1
                NNB=1
                DO 620 I=1,30
                        DO 620 J=1,30
                                DO 620 JJ=1,3
                                IF(RID(I,J,JJ).NE.IEL) GO TO
620
                                        IF(RI(I).EQ.0)GO TO
610
```

```
                                                    IF(RI(J).EQ.0) GO TO
     615
                                                    BRA=1.0
                                                    IPP=MINO(I,J)
                                                    IQQ=MAXO(I,J)
                                                    GO TO 625
     610                                            IF(RI(J).EQ.0) GO TO
     615
                                                    RI(I)=1.0
                                                    IPP=J
                                                    IQQ=I
                                                    GO TO 625
     615                                            RI(I)=1.0
                                                    RI(J)=1.0
                                                    IPP=I
                                                    IQQ=J
                                                    GO TO 625
     620            CONTINUE
     ****************************************************************
     C       SEARCH FOR MUTUAL COUPLING IN ZERO SEQUENCE
     ****************************************************************
     625            IDD(1)=IEL
                    DO 650 I=1,NN
                           DM=IEL
                           IF(REAL(ZM(I,1)).EQ.DM)MUT=1
                           IF(AIMAG(ZM(I,1)).EQ.DM)MUT=1
                           IF(MUT.NE.1)GO TO 650
                           MUT=0
                           II1=IFIX(REAL(ZM(I,1)))
                           II2=IFIX(AIMAG(ZM(I,1)))
                           IF(ID(II1).EQ.0)GO TO 650
                           IF(ID(II2).EQ.0)GO TO 650
                           IF(II1.EQ.IEL)GO TO 630
                           II3=II1
                           II1=II2
                           II2=II3
     630                   IDD(1)=II1
                           NNB=NNB+1
                           IDD(NNB)=II2
                           DM=II2
                           DO 645 J1=1,NN

     IF(REAL(ZM(J1,1)).EQ.DM)MUT=1

     IF(AIMAG(ZM(J1,1)).EQ.DM)MUT=
     1
                                          IF(MUT.NE.1) GO TO 645
                                          MUT=0
                                          III1=IFIX(REAL(ZM(J1,1)))
                                          III2=IFIX(AIMAG(ZM(J1,1)))
                                          IF(ID(III1).EQ.0)GO TO 645
```

```
                                        IF(ID(III2).EQ.0)GO TO 645
                                        IF(III1.EQ.DM) GO TO 643
                                        III3=III1
                                        III1=III2
                                        III2=III1
643                                     IF(III2.EQ.II1) GO TO 645
                                        NNB=NNB+1
                                        IDD(NNB)=III2
645                             CONTINUE
650                     CONTINUE
                        DO 660 I=1,NNB
                                ZMU(I,I)=ZD(IDD(I),3)
                                DO 660  J=1,NNB
                                        DD1=IDD(I)
                                        DD2=IDD(J)
                                        DO 660  KK=1,NN

IF(ZM(KK,1).EQ.CMPLX(
DD1,DD2))
        1MUT=1

IF(ZM(KK,1).EQ.CMPLX(DD2,DD1)
) MUT=1
                                        IF(MUT.NE.1)GO TO 660
                                                MUT=0
                                                ZMU(I,J)=ZM(KK,2)
                                                ZMU(J,I)=ZM(KK,2)
660                     CONTINUE
*****************************************************************
C       ZMU IS FORMED
*****************************************************************
                        DO 665 I=1,NNB
                        DO 665 J=1,NNB
                        PRINT 663,I,J,ZMU(I,J)
663                     FORMAT(2I,2F)
665                     CONTINUE
*****************************************************************
                        CALL CMXINV(ZMU,5,NNB)
*****************************************************************
                        DO 668 I=1,NNB
                        PRINT 667,(ZMU(I,J),J=1,NNB)
667                     FORMAT(10F)
668                     CONTINUE
                        DO 695 IL=1,IB
                        IF(NNB.EQ.1) GO TO 681
                        ZBB=CMPLX(0.0,0.0)
                                DO 680  J4=1,NNB
                                        J=J4+1
                                        I=IDD(J)
                                        IF(I.EQ.0) GO TO 680
                                        DO 670 I1=1,30
```

```
                                                    DO 670 I2=1,30
                                                           DO 670
      I3=1,3

      IF(RI
      D(I1,I2,I3
              1).NE.I)GO TO 670

      IP=I1

      IQ=I2
              ZBB=(ZMU(1,J)/ZMU(1,1))*(ZBO(IP,IL)-ZBO(IQ,IL))+ZBB
670                                  CONTINUE
680                           CONTINUE
681                           IF(BRA.NE.0) GO TO 686
                              IF(IQQ.EQ.IL) GO TO 690
                              ZBR(IL)=ZBO(IPP,IL)+ZBB
                              GO TO 690
686                           ZL(IL)=ZBB+ZBO(IPP,IL)-ZBO(IQQ,IL)
690                           CONTINUE
695                    CONTINUE
                       ZBB=CMPLX(0.0,0.0)
                       IF(BRA.NE.0) GO TO 750
                       DO 700 IL=1,IB
                              ZBO(IQQ,IL)=ZBR(IL)
                              ZBO(IL,IQQ)=ZBR(IL)
700                    CONTINUE
                       IF(NNB.EQ.1) GO TO 740
                       DO 730 J=2,NNB
                              I=IDD(J)
                              DO 720  I1=1,30
                                     DO 720 I2=1,30
                                            DO 720 I3=1,3
                              IF(RID(I1,I2,I3).NE.I) GO TO 720
                                                    IP=I1
                                                    IQ=I2
720                           CONTINUE

      ZBB=(ZMU(1,J)*(ZBO(IP,IQQ)-ZBO(IQ,IQQ
      ))/
              1ZMU(1,1))+ZBB
730                    CONTINUE
740                    ZBO(IQQ,IQQ)=ZBO(IPP,IQQ)+ZBB+1.0/ZMU(1,1)
                       ZBB=CMPLX(0.0,0.0)
                       GO TO 800
750                    IF(NNB.EQ.1) GO TO 781
                       DO 780 J=2,NNB
                              I=IDD(J)
                              DO 770  I1=1,30
                                     DO 770  I2=1,30
                                            DO 770  I3=1,3
```

```
                                                        IF(RID(I1,
     1I2,I3).NE.I)GO TO 770
                                                        IP=I1
                                                        IQ=I2
770                     CONTINUE

ZBB=(ZMU(I,J)*(ZL(IP)-ZL(IQ))/ZMU(1,1
))+ZBB
780             CONTINUE
781             ZLL=ZL(IPP)-ZL(IQQ)+ZBB+(1.0/ZMU(1,1))
                ZBB=CMPLX(0.0,0.0)
                DO 790 IP=1,IB
                DO 790 IQ=1,IB
                                        IF(IP.GT.IQ)GO TO 790

ZBO(IP,IQ)=ZBO(IP,IQ)-(ZL(IP)
*ZL(IQ)
     1/ZLL)
                                        IF(IP.EQ.IQ) GO TO 790
                                        ZBO(IQ,IP)=ZBO(IP,IQ)
790     CONTINUE
800             DO 850 I=1,5
                DO 850 J=1,5
                        ZMU(I,J)=CMPLX(0.0,0.0)
                        IDD(I)=0
850             CONTINUE
                DO 900 I=1,IB
                DO 900 J=1,IB
                        PRINT 880,I,J,ZBO(I,J)
880                     FORMAT(2I,2F)
900             CONTINUE
                NNB=1
1000    CONTINUE
*****************************************************************
******
C               ZBUS ZERO IS FORMED
*************************************************
        OPEN(UNIT=33,FILE='ZBUS.FOR')
        DO 1010 I=1,IB
        DO 1010 J=1,IB
        WRITE(33,1005)I,J,ZBO(I,J),ZB(I,J),ZB(I,J)
1005    FORMAT(2I,6F)
        PRINT 1007
1007    FORMAT(3X,'BUS  TO BUS ',3X,'ZERO SEQ ',5X,'POS
SEQ')
        PRINT 1008,I,J,ZBO(I,J),ZB(I,J)
1008    FORMAT(2I6,4F)
1010    CONTINUE
        CLOSE(UNIT=32)
*************************************************
C       NOW TO ADD ALL LOADS. ALL LOADS WILL BE LINKS WITH
```

```
NO
C       MUTUAL COUPLING.
**********************************************************
        DO 1200 I=1,IB
                IF(CABS(ZG(I)).EQ.0)GO TO 1200
                DO 1100 IL=1,IB
                        ZL(IL)=-ZB(I,IL)
                        ZLO(IL)=-ZBO(I,IL)
1100            CONTINUE
                ZLL=-ZL(I)+ZG(I)
                ZLLO=-ZLO(I)+ZGO(I)
                DO 1150 J=1,IB
                        DO 1150 K=1,IB
                                IF(J.GT.K)GO TO 1150

ZB(J,K)=ZB(J,K)-ZL(J)*ZL(K)/Z
LL
                                ZB(K,J)=ZB(J,K)

ZBO(J,K)=ZBO(J,K)-ZLO(J)*ZLO(
K)/ZLLO
                                ZBO(K,J)=ZBO(J,K)
1150            CONTINUE
1200    CONTINUE
        OPEN(UNIT=34,FILE='ZBUS.DAT')
        DO 1300 I=1,IB
                DO 1300 J=1,IB
        WRITE(34,1250)I,J,ZB(I,J),ZBO(I,J)
1250    FORMAT(2I,4F)
1300    CONTINUE
        CLOSE(UNIT=34)
        CLOSE(UNIT=33)
        OPEN(UNIT=36,FILE='MUT.CO')
        DO 1400 I=1,NN
                EL1=REAL(ZM(I,1))
                IF(EL1.EQ.0.0)GO TO 1322
                EL2=AIMAG(ZM(I,1))
                IEL1=IFIX(EL1)
                IEL2=IFIX(EL2)
                DO 1320 I1=1,IB
                DO 1320 J1=1,IB
                DO 1320 K1=1,IB
                IF(RID(I1,J1,K1).EQ.EL1)GO TO 1310
                IF(RID(I1,J1,K1).EQ.EL2)GO TO 1315
                GO TO 1320
1310            IBII=I1
                IBIJ=J1
                GO TO 1320
1315            IBJI=I1
                IBJJ=J1
1320            CONTINUE
```

```
1322    IF(EL1.EQ.0)GO TO 1400

WRITE(36,1350)EL1,EL2,IBII,IBIJ,IBJI,IBJJ,ZM(
I,2)
1350            FORMAT(2F,4I3,2F)
1400    CONTINUE
        WRITE(36,1450)
1450    FORMAT('  0.0 0.0 0 0 0 0 0.0 0.0')
        CLOSE(UNIT=36)
        STOP
        END
C       TITLE:CMXINV;SUBROUTINE FOR INVERT COMPLEX MATRIX
        SUBROUTINE CMXINV(A,MDIM,N)
        COMPLEX A(MDIM,N),BIGA,HOLD
        INTEGER L(100),M(100)
C
C       CONVERTED FROM SSP ROUTNE MINV
C
        DO 80 K=1,N
        L(K)=K
        M(K)=K
        BIGA=A(K,K)
        DO 20 J=K,N
        DO 20 I=K,N
10      IF(CABS(BIGA)-CABS(A(I,J))) 15,20,20
15      BIGA=A(I,J)
        L(K)=I
        M(K)=J
20      CONTINUE
        J=L(K)
        IF(J-K) 35,35,25
25      DO 30 I=1,N
        HOLD=-A(K,I)
        A(K,I)=A(J,I)
30      A(J,I)=HOLD
35      I=M(K)
        IF(I-K) 45,45,38
38      DO 40 J=1,N
        HOLD=-A(J,K)
        A(J,K)=A(J,I)
40      A(J,I)=HOLD
45      DO 55 I=1,N
        IF(I-K) 50,55,50
50      A(I,K)=A(I,K)/(-BIGA)
55      CONTINUE
        DO 65 I=1,N
        HOLD=A(I,K)
        DO 65 J=1,N
        IF(I-K) 60,65,60
60      IF(J-K) 62,65,62
62      A(I,J)=HOLD*A(K,J)+A(I,J)
```

```
65      CONTINUE
        DO 75 J=1,N
        IF(J-K) 70,75,70
70      A(K,J)=A(K,J)/BIGA
75      CONTINUE
        A(K,K)=(1.0000000,0.0000000)/BIGA
80      CONTINUE
        K=N
100     K=K-1
        IF(K) 150,150,105
105     I=L(K)
        IF(I-K) 120,120,108
108     DO 110 J=1,N
        HOLD=A(J,K)
        A(J,K)=-A(J,I)
110     A(J,I)=HOLD
120     J=M(K)
        IF(J-K) 100,100,125
125     DO 130 I=1,N
        HOLD=A(K,I)
        A(K,I)=-A(J,I)
130     A(J,I)=HOLD
        GO TO 100
150     RETURN
        END
*************************************************************
C       TITLE:FALT.F4;TAKES DATA FROM ZBUS.DAT AND COMPUTES
C                     ALL FAULT CURRENTS AT ALL BUSES
*************************************************************
        DIMENSION
ZB(30,30),ZBO(30,30),FCUR(300,3,2),EFALT(30,3,2)
        1,EB(30),IDELE(300),EIB(30)
        COMPLEX
ZB,ZBO,FCUR,EFALT,EB,EB1,ZB1,ZBO1,ZR1,ZN1,ZNI,ZNJ,
        1ZR2,ZN2,ZF,IDELE,FCUR1,FCUR2,ALCUR
        OPEN(UNIT=34,FILE='TEST.DAT')
        OPEN(UNIT=35,FILE='ZBUS.DAT')
        READ(34,5) IB,E1
5       FORMAT(I,F)
        IBB=IB*IB
        DO 7 I=1,IB
        EB(I)=CMPLX(E1,0.0)
7       CONTINUE
9       READ(34,10),NI,I,J,K
10      FORMAT(4I)
        IF(NI.EQ.0)GO TO 15
        IF(K.EQ.2)I=-I
        IF(K.EQ.3)J=-J
        RI=I
        RJ=J
        IDELE(NI)=CMPLX(RI,RJ)
```

```
            IF(NI.NE.0)GO TO 9
15          DO 30 II=1,IBB
            READ(35,25)I,J,ZB1,ZBO1
25          FORMAT(2I,4F)
            ZB(I,J)=ZB1
            ZBO(I,J)=ZBO1
30          CONTINUE
            CLOSE(UNIT=35)
            OPEN(UNIT=37,FILE='MUT.CO')
            OPEN(UNIT=38,FILE='FALT.DAT')
            OPEN(UNIT=39,FILE='EFLT.DAT')
            OPEN(UNIT=40,FILE='RELA.DAT')
            OPEN(UNIT=41,FILE='FCUR.DAT')
            OPEN(UNIT=42,FILE='DSK.XFR')
            OPEN(UNIT=43,FILE='LCUR.DAT')
            READ(40,32) RMVAB,RKVBA,IRR
32          FORMAT(2F,I)
            RKVBA=RKVBA*1E3
            FIPU=RMVAB*1E6/(SQRT(3.0)*RKVBA)
33          READ(40,34)IRR
34          FORMAT(I)
            IF(IRR.NE.0)GO TO 33
36          READ(40,37)J,E
37          FORMAT(I,F)
            IF(J.EQ.0)GO TO 38
            EIB(J)=E
            GO TO 36
38          TYPE 35
35          FORMAT(' ENTER THE FAULT
IMPEDENCE-REAL(SP)IMAGINARY..,')
            ACCEPT 40,ZF
40          FORMAT(2F)
            DO 500 IFLT=1,IB
            IF(CABS(ZB(IFLT,IFLT)).EQ.0)GO TO 500
                    DO 50 I=1,IB
                            IF(I.EQ.IFLT)GO TO 45

EFALT(I,2,1)=SQRT(3.0)*(EB(I)-((ZB(I,
IFLT)*EB
           1(IFLT))/(ZF+ZB(IFLT,IFLT))))

EFALT(I,1,2)=-(SQRT(3.0)*EB(IFLT)*ZBO
(I,IFLT)/
           1(ZBO(IFLT,IFLT)+3*ZF+(2*ZB(IFLT,IFLT))))

EFALT(I,2,2)=SQRT(3.0)*EB(I)-((SQRT(3
 .0)*EB

1(IFLT)*ZB(I,IFLT))/(ZBO(IFLT,IFLT)+(2*(ZB(IFLT,IFLT)
)+3*ZF)))
```

```
EFALT(I,3,2)=EFALT(I,2,2)-(SQRT(3.0)*
EB(I))
                        GO TO 50
45
EFALT(IFLT,2,1)=SQRT(3.0)*(ZF*EB(IFLT
)/(ZF+
     1ZB(IFLT,IFLT)))

EFALT(IFLT,1,2)=-SQRT(3.0)*EB(IFLT)*Z
BO(IFLT,
     1IFLT)/(ZBO(IFLT,IFLT)+(2*ZB(IFLT,IFLT))+3*ZF)

EFALT(IFLT,2,2)=SQRT(3.0)*EB(IFLT)*(Z
BO(IFLT,

1IFLT)+ZB(IFLT,IFLT)+3*ZF)/(ZBO(IFLT,IFLT)+(2*ZB(IFLT
,IFLT))+3*
     2ZF)

EFALT(IFLT,3,2)=-SQRT(3.0)*EB(IFLT)*Z
B(IFLT,IFL
     1T)/(ZBO(IFLT,IFLT)+(2*ZB(IFLT,IFLT))+3*ZF)
50              CONTINUE
                REWIND 34
                REWIND 37

WRITE(39,53)(IFLT,I,EFALT(I,2,1),EFALT(I,1,2)
,
     1EFALT(I,2,2),EFALT(I,3,2),I=1,IB)
53              FORMAT(2I3,8F)
                READ(34,55)II,E
55              FORMAT(I,F)
                DO 90 K=1,IBB
                READ(34,60)NN,I,J,KK,ZR1,ZN1,ZNI,ZNJ
60              FORMAT(4I,8F)
                IF(NN.EQ.0)GO TO 91
                FCUR(NN,2,1)=(EFALT(I,2,1)-EFALT(J,2,1))/ZR1

FCUR(NN,1,2)=(EFALT(I,1,2)-EFALT(J,1,2))/(ZN1
+3*
     1(ZNI+ZNJ))
                FCUR(NN,2,2)=(EFALT(I,2,2)-EFALT(J,2,2))/ZR1
                FCUR(NN,3,2)=(EFALT(I,3,2)-EFALT(J,3,2))/ZR1
                        DO 85 I2=1,IBB

READ(37,65)RN1,RN2,IBII,IBIJ,
IBJI,IBJJ
     1,ZN2
65                                  FORMAT(2F,4I,2F)
                                    NN1=IFIX(RN1)
                                    NN2=IFIX(RN2)
```

```
                                        IF(NN1.EQ.NN)GO TO 70
                                        IF(NN2.EQ.NN) GO TO 74
                                        IF(NN1.EQ.0)GO TO 86
                                        GO TO 85
70      FCUR(NN,1,2)=((EFALT(IBJI,1,2)-EFALT(IBJJ,1,2))/
        1(ZN2))+FCUR(NN,1,2)
                                        GO TO 85
74      FCUR(NN,1,2)=((EFALT(IBII,1,2)-EFALT(IBIJ,1,2))/
        1(ZN2))+FCUR(NN,1,2)
85                      CONTINUE
86                      REWIND 37
90              CONTINUE
91              REWIND 34
                DO 300 NN=1,IBB
                        IF(CABS(FCUR(NN,2,1)).EQ.0)GO TO 300

WRITE(38,250)IFLT,NN,FCUR(NN,2,1),FCU
R(NN,1,2)
        1,FCUR(NN,2,2),FCUR(NN,3,2)
250                     FORMAT(2I3,8F)
300             CONTINUE
                DO 400 NN=1,IBB
                        IF(CABS(FCUR(NN,2,1)).EQ.0)GO TO 400

FCUR1=(RKVBA/EIB(IFIX(ABS(REAL(IDELE(
NN)
        1)))))*FCUR(NN,2,1)

FCUR2=(RKVBA/EIB(IFIX(ABS(REAL(IDELE(
NN)
        1)))))*(FCUR(NN,1,2)+FCUR(NN,2,2)+FCUR(NN,3,2))
                        FCUR1=FCUR1*FIPU
                        FCUR2=FCUR2*FIPU
                        IRI=(IFIX(REAL(IDELE(NN))))
                        IRJ=(IFIX(AIMAG(IDELE(NN))))
                        CUR1=CABS(FCUR1)
                        CUR2=CABS(FCUR2)
                        IF(CUR1.LT.0.001) GO TO 400
                        WRITE(41,350)IFLT,NN,CUR1,CUR2
350                     FORMAT(2I,2F)
400             CONTINUE
500     CONTINUE
        DO 600 I=1,IBB
        READ(42,525)IL,JL,ALCUR
        IF(IL.EQ.0)GO TO 610
        IF(REAL(ALCUR).LE.0.0)GO TO 600
        BLCUR=CABS(ALCUR)
        CLCUR=FIPU*BLCUR*RKVBA/EIB(JL)
        BLCUR=FIPU*BLCUR*RKVBA/EIB(IL)
        WRITE(43,525)IL,JL,BLCUR,CLCUR
525     FORMAT(2I,2F)
```

```
600     CONTINUE
610     WRITE(41,602)
        WRITE(43,602)
602     FORMAT(' 0 0 0 0 0 ')
        CLOSE(UNIT=36)
        CLOSE(UNIT=37)
        CLOSE(UNIT=38)
        CLOSE(UNIT=39)
        CLOSE(UNIT=42)
        CLOSE(UNIT=43)
        STOP
        END
```

```
*********************************************************
C       TITLE:COORD.F4;USES DATA FROM INPUT.F4,FALT.F4 TO
COORDINATE
C       THE PROTECTION DEVICES FOR THE WHOLE DISTRIBUTION
SYSTEM.
*********************************************************
        OPEN(UNIT=30,FILE='RELA.DAT')
        OPEN(UNIT=31,FILE='LOCUR.DAT')
        OPEN(UNIT=32,FILE='LCUR.DAT')
        OPEN(UNIT=33,FILE='FCUR.DAT')
        OPEN(UNIT=34,FILE='TEST.DAT')
        OPEN(UNIT=35,FILE='XFOR.DAT')
        OPEN(UNIT=36,FILE='DEV.DAT')
        OPEN(UNIT=37,FILE='ADEV.DAT')
        DIMENSION EB(30),CUREL(200),CURLO(30),Z(100)
        1,AIDEVL(30,4),AIDEV(100,7),XFR(200,2),IID(3),RID(100
)
        2,DEV(20,0/4)
        COMPLEX Z,AIDEV,C1,C2,Z1,Z2,RID,CUREL,CU1,CURLO,XFR
*********************************************************
C       READ IN LOAD AND BUS VOLTAGE DATA
*********************************************************
        READ(30,5)R
5       FORMAT(F)
        READ(34,10)IB,E1
10      FORMAT(I,F)
11      READ(30,12)I
12      FORMAT(I)
        IF(I.NE.0)GO TO 11
13      READ(30,14)I,E1
14      FORMAT(I,F)
        IF(I.EQ.0)GO TO 15
        EB(I)=E1
        GO TO 13
15      DO 20 I=1,IB
        READ(31,16)J,CU2
16      FORMAT(I,F)
        IF(J.EQ.0)GO TO 21
        CURLO(J)=CMPLX(CU2*1.25,0.0)
20      CONTINUE
21      DO 24 I=1,20
        READ(36,22)K,(DEV(I,J),J=0,4)
        IF(K.EQ.0)GO TO 23
22      FORMAT(I,5F)
24      CONTINUE
*********************************************************
C       NOW TO SET ALL LOAD DEVICES
*********************************************************
23      TYPE 25
```

```
25      FORMAT(' ALL LOAD CURRENTS ARE READY,USE DEVICE
NUMBER LIST,')
        DO 100 I=1,IB
        IF(CABS(CURLO(I)).EQ.0)GO TO 100
        ID=I
30      TYPE 35,ID
35      FORMAT(' SELECT THE DEVICE FOR THE LOAD AT
BUS',I3,'..,'$)
        ACCEPT 40,IDEV
        AIDEVL(ID,1)=FLOAT(IDEV)
40      FORMAT(I)
        CURLI=REAL(CURLO(I))
        CALL
SELECT(CURLI,EB(I),AIDEVL(I,1),AIDEVL(I,2),AIDEVL(I,3)
        1,AIDEVL(I,4))
100     CONTINUE
**************************************************
C       NOW TO BEGIN COORDINATING ELEMENTS IN THE
DISTRIBUTION
**************************************************
110     READ(34,120)NN,I,J,K,R,X
120     FORMAT(4I,2F)
        IF(NN.EQ.0)GO TO 130
        NE=NN
        CI=I
        CJ=J
        RID(NN)=CMPLX(CI,CJ)
        Z(NN)=CMPLX(R,X)
        GO TO 110
130     DO 140 IE=1,NE
        READ(32,135)I,J,CU1
135     FORMAT(2I,2F)
        IF(I.EQ.0)GO TO 140
        IA=0
        CALL SERCH(NE,RID,IE,I,J,IA,IID)
        Z1=0.0*Z1
        Z2=0.0*Z2
                DO 136 IEL=1,IA
                Z1=1/(Z2+Z(IID(IEL)))
                Z2=1/Z1
136             CONTINUE
                DO 138  IEL=1,IA
                CUREL(IID(IA))=(Z2)*(1/Z(IID(IEL)))*CU1
138             CONTINUE
                IF(IA.GT.1)TYPE 101,J
101             FORMAT(' CAUTION THERE IS MORE THAN ONE
SOURCE
        1OF POWER TO THE BUS'I4)
140     CONTINUE
```

```
      DO 150  I=1,NE
              READ(35,145)IJ,J,TINRSH,TWST1,TWST2,TS1
145           FORMAT(2I,4F)
              IF(IJ.EQ.0)GO TO 151
              CALL SERCH(NE,RID,I,IJ,J,IA,IID)
              IA=1
147                   XFR(IID(IA),1)=CMPLX(TS1,TINRSH)
                      XFR(IID(IA),2)=CMPLX(TWST1,TWST2)
      IA=0
150   CONTINUE
*************************************************
C     NOW TO DETERMINE WHAT ELEMENTS HAVE LOAD BUSSES
CONNECTED
*************************************************
151   DO 190  I=1,NE
              IR=IFIX(REAL(RID(I)))
              IM=IFIX(AIMAG(RID(I)))
              IF(AIDEVL(IR,1).NE.0) GO TO 155
              IF(AIDEVL(IM,1).NE.0)GO TO 156
              GO TO 190
155           II=IFIX(REAL(RID(I)))
              JJ=IFIX(AIMAG(RID(I)))
              GO TO 157
156           II=IFIX(AIMAG(RID(I)))
              JJ=IFIX(REAL(RID(I)))
157           CII=II
              CJJ=JJ
              AIDEV(I,1)=CMPLX(CJJ,CII)
              AIDEV(I,2)=CMPLX(0.0,AIDEVL(II,1))
              AIDEV(I,4)=CMPLX(AIDEVL(II,2),AIDEVL(II,3))
              IF(AIDEVL(II,1).GE.35)AIDEV(I,5)=CMPLX(0.0,
     1AIDEVL(II,4))
      IF(AIDEVL(II,1).LT.0)AIDEV(I,7)=CMPLX(0.0,AIDEVL(II,4
     ))
159           TYPE 158,JJ,II
158           FORMAT(' SELECT DEVICE FOR
     BUS',I3,'PROTECTING ELEMENT
      1FEEDING'//' LOAD AT BUS',I4,'..,'$)
              ACCEPT 160,IDEV
160   FORMAT(I)
              AIDEV1=FLOAT(IDEV)
              DURR=AIMAG(AIDEV(I,4))
              CURR=REAL(AIDEV(I,4))
              IF(AIMAG(AIDEV(I,2)).GT.0)CURR=10**(DURR)
              CURR=REAL(CUREL(I))
      CALL SELECT(CURR,EB(JJ),AIDEV1,AIDEV2,AIDEV3,CT1)
              CALL
     SETDEV(CUREL,I,JJ,II,AIDEV1,AIDEV2,AIDEV3,
      1AIDEV,XFR(I,1),XFR(I,2),RE,EB(JJ),EB(II),RID,CT1,DEV
```

```
)
                CT1=0.0
                IF(RE.NE.0)GO TO 159
190       CONTINUE
          IEL=0
200       NEL=NE-IEL
          IF(REAL(AIDEV(NEL,1)).NE.0)GO TO 300
          INDEX=1
          I=IFIX(REAL(RID(NEL)))
          J=IFIX(AIMAG(RID(NEL)))
          IF(AIMAG(AIDEV(NEL,2)).NE.0)GO TO 250
205       TYPE 210,J,NEL
          RE=0
210       FORMAT(' ENTER THE DEVICE   FOR THE BUS',I3,'OF
ELEMENT',I4)
          ACCEPT 230,IDEV
230       FORMAT(I)
          IF(IDEV.EQ.100)GO TO 400
          AIDEV1=FLOAT(IDEV)
          CURR=AIMAG(CUREL(NEL))
          CALL SELECT(CURR,EB(J),AIDEV1,AIDEV2,AIDEV3,CT1)
          IF(AIDEV1.GT.34)AIDEV(NEL,5)=CMPLX(0.0,.414973)
          CALL SETDEV(CUREL,NEL,I,J,AIDEV1,AIDEV2,AIDEV3,
          1AIDEV,XFR(NEL,1),XFR(NEL,2),RE,EB(I),EB(J),RID,CT1,D
EV)
          IF(RE.NE.0)GO TO 205
250       TYPE 210,I,NEL
          ACCEPT 230,IDEV
          AIDEV1=FLOAT(IDEV)
          RE=0
          CURR=REAL(CUREL(NEL))
          CALL SELECT(CURR,EB(I),AIDEV1,AIDEV2,AIDEV3,CT1)
          IF(AIDEV1.GT.34)AIDEV(NEL,5)=AIDEV(NEL,5)+CMPLX(.4149
73,0.0)
          CALL SETDEV(CUREL,NEL,I,J,AIDEV1,AIDEV2,AIDEV3,
          1AIDEV,XFR(NEL,1),XFR(NEL,2),RE,EB(I),EB(J),RID,CT1,D
EV)
          IF(RE.NE.0)GO TO 250
300       IEL=IEL+1
          IF(IEL.LT.NE) GO TO 200
          IF(INDEX.EQ.0)GO TO 400
          IEL=0
          INDEX=0
          GO TO 200
400       TYPE 410
          PRINT 410
410       FORMAT(' DEVICE LISTING')
          DO 440 I=1,NE
          TYPE 420,I,(AIDEV(I,J),J=1,7)
```

```
      PRINT 420,I,(AIDEV(I,J),J=1,7)
      WRITE(37,420)I,(AIDEV(I,J),J=1,7)
420   FORMAT(I,14F)
440   CONTINUE
      WRITE(37,442)
442   FORMAT(' 0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0
0.0
     1 0.0 0.0 0.0')
2000  CLOSE(UNIT=30)
      CLOSE(UNIT=31)
      CLOSE(UNIT=32)
      CLOSE(UNIT=33)
      CLOSE(UNIT=34)
      CLOSE(UNIT=36)
      CLOSE(UNIT=37)
      STOP
      END
*****************************************************
*****************************************************
C     SUBROUTINE SERCH;FINDS THE ELEMENT CORRESPONDING TO
TWO
C              BUSSES.
*****************************************************
      SUBROUTINE SERCH(NE,RID,NN,I,J,IA,IID)
      DIMENSION RID(100),IID(3)
      COMPLEX RID,C1,C2
      IA=0
      DO 30    IEL=1,100
               CJ=J
               CI=I
               C1=CMPLX(CI,CJ)
               C2=CMPLX(CJ,CI)
               IF(RID(IEL).EQ.C1)GO TO 20
               IF(RID(IEL).EQ.C2)GO TO 20
               GO TO 30
20    IA=IA+1
      IID(IA)=IEL
30    CONTINUE
31    RETURN
      END
*****************************************************
*************************************************
C     SUBROUTINE REFALT;READS FCUR.DAT TO OUTPUT FAULT
CURRENTS
C              AT THE BUSSES
*************************************************
      SUBROUTINE REFALT(IFALT,NEL,FALT,CUREL)
10    READ(33,15)IEF,NN,TFAL,SFAL
15    FORMAT(2I,2F)
```

```
          IF(IEF.EQ.0)GO TO 20
          IF(IEF.NE.IFALT)GO TO 10
          IF(NN.NE.NEL)GO TO 10
          FALT1=TFAL
          FALT2=SFAL
          FALT=AMIN1(FALT1,FALT2)
          FLOCUR=3.0*CUREL
          IF(FALT.LE.FLOCUR)FALT=AMAX1(FALT1,FALT2)
          FALT=AMAX1(FALT1,FALT2)
20        REWIND 33
          RETURN
          END
*****************************************************
C         SUBROUTINE SETDEV; SETS THE DEVICE INSTANTANEOUS
ELEMENT
C                 DEPENDING ON THE FAULT CURRENT AT THAT BUS
DOES
C                 COORDINATE WITH OTHER DEVICES
*****************************************************
          SUBROUTINE
SETDEV(CUREL,IEL,I,J,AIDEV1,AIDEV2,AIDEV3,AIDEV
          1,XFR1,XFR2,RE,EB1,EB2,RID,CT,DEV)
          DIMENSION
AIDEV(100,7),CUREL(100),DEV(20,0/4),RID(100)
          COMPLEX AIDEV,XFR1,XFR2,CUREL,RID
          IDEV1=IFIX(AIDEV1)
30        IF(IDEV1.LT.0)CALL
SETREL(CUREL,IEL,I,J,AIDEV,AIDEV1,
          1AIDEV2,AIDEV3,XFR1,XFR2,RE,EB1,EB2,RID,CT,DEV)
          IF(IDEV1.LT.0)GO TO 100
          IF(IDEV1.EQ.99)GO TO 100
          IF(IDEV1.LT.35.AND.IDEV1.GT.0)CALL SETFUS(CUREL(IEL
          1),I,J,IEL,AIDEV,IDEV1,AIDEV2,AIDEV3,XFR1,XFR2,RE,EB1
,EB2,
          2DEV,RID)
          IF(IDEV1.GE.35.AND.IDEV1.LT.99)CALL
SETCKB(CUREL(IEL),
          1I,J,IEL,AIDEV,IDEV1,AIDEV2,AIDEV3,CT,EB1,EB2)
100       RETURN
          END
*****************************************************
*****************************************************
C         SUBROUTINE SETFUS;COORDINATES AND SELECTS A FUSE
*****************************************************
          SUBROUTINE
SETFUS(CUREL,I,J,IEL,AIDEV,IDEV1,AIDEV2,AIDEV3
          1,XFR1,XFR2,RE,EB1,EB2,DEV,RID)
          DIMENSION
AIDEV(100,6),CUREL(100),DEV(20,0/4),RID(100)
```

```
      COMPLEX AIDEV,XFR1,XFR2,CUREL,RID
      JJ=IFIX(AIMAG(AIDEV(IEL,2)))
      IF(JJ.EQ.0)CALL XFDEV(1,J,IEL,AIDEV,COOF)
      IF(JJ.NE.0)CALL XFDEV(2,J,IEL,AIDEV,COOF)
      IF(JJ.EQ.0)CURR=AIMAG(CUREL(IEL))
      IF(JJ.NE.0)CURR=REAL(CUREL(IEL))
      IF(JJ.EQ.0.AND.COOF.LT.CURR)COOF=CURR
      IF(JJ.NE.0)COOF=(EB2/EB1)*COOF
      IF(JJ.NE.0.AND.COOF.LT.CURR)COOF=CURR
      IF(IDEV1.LE.15) CALL SFUSE(COOF,IDEV1,OFSET,OFSET1)
      IF(IDEV1.GT.15) CALL SBORFU(COOF,IDEV1,OFSET,OFSET1)
      IF(JJ.EQ.0) GO TO 20
      CI=I
      CJ=J
      AIDEV(IEL,1)=CMPLX(CI,CJ)
      AIDEV(IEL,2)=AIDEV(IEL,2)+CMPLX(FLOAT(IDEV1),0.0)
      AIDEV(IEL,3)=CMPLX(OFSET,OFSET1)
      GO TO 25
20    CI=I
      CJ=J
      AIDEV(IEL,1)=CMPLX(CI,CJ)
      AIDEV(IEL,2)=CMPLX(0.0,FLOAT(IDEV1))
      AIDEV(IEL,4)=CMPLX(OFSET,OFSET1)
      GO TO 50
25    IF(CABS(XFR1).EQ.0)GO TO 50
      AX=ALOG10((AIMAG(XFR1))/3.0)
      IF(REAL(AIDEV(IEL,2)).LE.15)GO TO 35
      IF(OFSET.LE.AX)CUR=10**AX
      IF(OFSET.LE.AX)CALL SBORFU(CUR,IDEV,OFSET,OFSET1)
      GO TO 40
35    IF(OFSET.LE.AX)CUR=10**AX
      IF(OFSET.LE.AX)CALL SFUSE(CUR,IDEV,OFSET,OFSET1)
40    AIDEV(IEL,2)=CMPLX(FLOAT(IDEV),AIMAG(AIDEV(IEL,2)))
      AIDEV(IEL,3)=CMPLX(OFSET,OFSET1)
      AR=ALOG10(REAL(XFR2))
      CALL FUSE(2,REAL(AIDEV(IEL,2)),AR,OFSET1,TVAL1)
      TVAL=10**TVAL1
      IF(TVAL.GT.2.0)GO TO 43
      GO TO 50
43    TYPE 45
45    FORMAT(' UNABLE TO PUT FUSE IN THIS LOCATION
     SUBSTITUE
     1ANOTHER DEVICE')
      RE=1.0
      GO TO 300
50    CALL REFALT(J,IEL,FALT,CUREL(IEL))
      PAUSE 55
      IF(JJ.EQ.0)CALL
     SFALT1(AIDEV,CUREL,RID,IEL,I,J,TVAL1,DEV,
```

```
          1CVAL)
          IF(JJ.NE.0)CALL SFALT2(AIDEV,IEL,I,J,TVAL1,DEV,
          1FALT,CVAL)
          PAUSE 60
          ADEV=FLOAT(IDEV1)
55        CALL FUSE(1,ADEV,CVAL,OFSET,TVAL)
          IF(TVAL.GT.TVAL1)GO TO 200
          ADEV=ADEV+1
          NEGDEV=-IFIX(ADEV)
          IF(ADEV.LE.15)CALL SFUSE(COOF,NEGDEV,OFSET,OFSET1)
          IF(ADEV.GT.15)CALL SBORFU(COOF,NEGDEV,OFSET,OFSET1)
          GO TO 55
200       IF(JJ.NE.0)GO TO 250
          AIDEV(IEL,2)=CMPLX(0.0,ADEV)
          AIDEV(IEL,4)=CMPLX(OFSET,OFSET1)
          GO TO 300
250       AIDEV(IEL,2)=CMPLX(ADEV,AIMAG(AIDEV(IEL,2)))
          AIDEV(IEL,3)=CMPLX(OFSET,OFSET1)
300       RETURN
          END
**************************************************
**************************************************
C         SUBROUTINE FUSE;COMPUTES TIME VALUE FOR A GIVEN LOAD
CURRENT
**************************************************
          SUBROUTINE FUSE(ID,ADEV,CVAL,OFSET,TVAL)
          TVAL=0.0
          IDEV=IFIX(ADEV)
          IF(IDEV.GT.15)GO TO 50
          X=CVAL-OFSET
          IF(ID.NE.1)GO TO 40
          TVAL=4.0480+(-36.4234*X)+(223.7526*(X**2))+(-751.279*
(X**3))
          1+(1347.01*(X**4))+(-1222.67*(X**5))+(440.813*(X**6))
          TVAL=TVAL-2.0
          GO TO 100
40        X=CVAL-OFSET+.1
          TVAL=6.426+(-37.922*X)+(121.909*(X**2))+(-213.420*(X*
*3))+
          1(201.771*(X**4))+(-96.9836*(X**5))+(18.6046*(X**6))
          TVAL=TVAL-2.0
          IF(X.GT.1.4)TVAL=-1.95
          GO TO 100
50        X=CVAL-OFSET
          IF(ID.NE.1)GO TO 70
          TVAL=3.87698+(-4.262768*X)+(1.219340*(X**2))
          TVAL=TVAL-2.0
          GO TO 100
70        X=CVAL-OFSET+.1
```

```
      TVAL=4.614840+(-6.183224*X)+(3.23181*(X**2))+(-.60571
36*(X**3))
      TVAL=TVAL-2.0
100   RETURN
      END
*************************************************
*************************************************
C     SUBROUTINE RELAY;COMPUTES TIME VALUE FOR A GIVEN
CURRENT
C              VALUE FOR A SPECIFIC RELAY
*************************************************
      SUBROUTINE RELAY(NDEV,CURR,TVAL,TDSET,DEV,AMST)
      DIMENSION DEV(20,0/4)
      TVAL=0.0
      X=ALOG10(CURR)
      IF(X.GT.1.2)X=1.2
      DO 10 I=0,4
      TVAL=TVAL+DEV(NDEV,I)*(X**I)
10    CONTINUE
      IF(NDEV.EQ.7)TVAL=TVAL-2.0
      TVAL=TVAL+TDSET
      IF(CURR.GT.AMST.AND.AMST.NE.0)TVAL=-2.0
      RETURN
      END
*************************************************
C     SUBROUTINE CKTBKR;COMPUTES TIME VALUE FOR A GIVEN
CURRENT
C              VALUE
*************************************************
      SUBROUTINE CKTBKR(ID,MDEV,DVAL,OFSET,TVAL,AMVAL)
      CVAL=DVAL-OFSET
      IF(ID.NE.1)GO TO 50
      CVAL=CVAL+.1122
      IF(AMVAL.EQ.0.0)AMVAL=10
      IF(CVAL.GT.AMVAL)GO TO 90
      TVAL=5.76908+(-10.88261*(CVAL))+(23.65419*(CVAL**2))+
(-34.7922
      1*(CVAL**3))+(33.77472*(CVAL**4))+(-21.14536*(CVAL**5
))+(6.4
      231778*(CVAL**6))
      TVAL=TVAL-2.0
      GO TO 100
50    CVAL=CVAL+.2315
      AMVAL=AMVAL+.075
      IF(CVAL.GT.AMVAL)GO TO 95
      TVAL=5.8596722+(-4.394335*CVAL)+(-.50690284*(CVAL**2)
)+(10.40
      12739*(CVAL**3))+(-17.064956*(CVAL**4))+(13.011543*(C
VAL**5))
```

```
     2+(-4.010724*(CVAL**6))
     TVAL=TVAL-2.0
     GO TO 100
90   TVAL=-2.0
     GO TO 100
95   TVAL=ALOG10(.025)
100  RETURN
     END
************************************************
************************************************
C    SUBROUTINE SETREL;COORDINATES AND SELECTS A RELAY
************************************************
     SUBROUTINE
SETREL(CUREL,IEL,I,J,AIDEV,AIDEV1,AIDEV2,AIDEV3,
     1XFR1,XFR2,RE,EB1,EB2,RID,CT,DEV)
     DIMENSION
AIDEV(100,7),IIDD(30),RID(100),IID(3),CUREL(100)
     1,DEV(20,0/4),FT(30,2)
     COMPLEX AIDEV,CUREL,XFR1,XFR2,RID
     COOF=0.0
     CURR=0.0
     CDUR=0.0
     TYPE 5
5    FORMAT(' DOES THIS RELAY HAVE AN INST. ELEMENT,IF
YES 0')
     ACCEPT 7,IL
7    FORMAT(I)
     JJ=IFIX(AIMAG(AIDEV(IEL,2)))
     MDEV=IFIX(-AIDEV1)
     IF(JJ.EQ.0)AIDEV(IEL,1)=CMPLX(FLOAT(I),FLOAT(J))
     IF(JJ.EQ.0)AIDEV(IEL,2)=CMPLX(0.0,AIDEV1)
     IF(JJ.NE.0)AIDEV(IEL,2)=CMPLX(AIDEV1,0.0)+AIDEV(IEL,2
)
     IF(JJ.EQ.0)CALL XFDEV(1,J,IEL,AIDEV,COOF)
     IF(JJ.NE.0)CALL XFDEV(2,J,IEL,AIDEV,COOF)
     IF(JJ.EQ.0)CURR=AIMAG(CUREL(IEL))
     IF(JJ.NE.0)CURR=REAL(CUREL(IEL))
     IF(JJ.EQ.0.AND.COOF.LT.CURR)COOF=CURR
     IF(JJ.NE.0)COOF=(EB2/EB1)*COOF
     CDUR=ALOG10(COOF)
     IF(JJ.NE.0.AND.COOF.LT.CURR)COOF=CURR
     IF(CDUR.GT.AIDEV2)AIDEV1=4.0
     IF(CDUR.GT.AIDEV2.AND.JJ.EQ.0)CALL
SELECT(COOF,EB2,AIDEV1,
     1AIDEV2,AIDEV3,CT)
     IF(CDUR.GT.AIDEV2.AND.JJ.NE.0)CALL
SELECT(COOF,EB1,AIDEV1,
     1AIDEV2,AIDEV3,CT)
     CURL=AIMAG(CUREL(IEL))
```

```
            IF(JJ.NE.0)AIDEV(IEL,3)=CMPLX(AIDEV2,AIDEV3)
            IF(JJ.EQ.0)AIDEV(IEL,4)=CMPLX(AIDEV2,AIDEV3)
            IF(JJ.NE.0)CURL=REAL(CUREL(IEL))
            IF(JJ.NE.0)AIDEV(IEL,7)=CMPLX(CT,0.0)+AIDEV(IEL,7)
            IF(JJ.EQ.0)AIDEV(IEL,7)=CMPLX(0.0,CT)
            IF(IL.NE.0)GO TO 100
            CALL REFALT(J,IEL,FALT1,CURL)
            IF(JJ.NE.0)GO TO 32
            FALT1=FALT1*(EB1/EB2)
            FALT1=FALT1/(10**(REAL(AIDEV(IEL,4))))
            IN=0
            DO 10 JI=1,30
                    CALL SERCH(1,RID,IEL,J,JI,IA,IID)
                    IF(IA.EQ.0)GO TO 10
                    DO 8 JA=1,IA
                            IN=IN+1
                            IIDD(IN)=IID(IA)
8                   CONTINUE
10          CONTINUE
            DO 30 INN=1,IN
                    ID=IIDD(INN)
                    IF(ID.EQ.IEL) GO TO 30
                    IJ=IFIX(AIMAG(RID(ID)))
                    CURJ=AIMAG(CUREL(ID))
                    CALL REFALT(IJ,ID,FALT,CURJ)
                    FALT2=ALOG10(FALT)
                    AID=REAL(AIDEV(ID,2))
                    IAID=IFIX(AID)
                    IF(IAID.GT.0)GO TO 16
                    IF(IAID.LT.0)FALT0=FALT/(10**(REAL(AIDEV(ID,3
))))
                    NDEV=-IFIX(REAL(AIDEV(ID,2)))
                    KFAL=IFIX(10*FALT0)
                    DO 15 K=15,KFAL,10
                            RK=K*.1
                            IF(ALOG10(RK).GT.1.2)GO TO 16
                            CALL
RELAY(NDEV,RK,TVAL1,REAL(AIDEV(ID,6))
           1,DEV,REAL(AIDEV(ID,5)))
                            CALL
RELAY(MDEV,RK,TVAL2,TMSET,DEV,0.0)
                            TIMEO=(10**TVAL1)+.4
                            TIMER=TVAL2
                            TIMES=ALOG10(TIMEO)
                            TMSET1=TIMES-TIMER
                            IF(TMSET1.LE.0)GO TO 15
                            TMSET=TMSET1+TMSET
15                  CONTINUE
16                  IF(IAID.LT.0)GO TO 25
```

```
                OFSET=AIMAG(AIDEV(ID,3))
                FNSET=FALT2-OFSET
                IF(FNSET.GT.1.5)FALT2=OFSET+1.5
                KVAL=IFIX(10*OFSET)
                KFAL=IFIX(10*FALT2)
                DO 20 K=KVAL,KFAL
                        RK=K*.1
        IF(AID.LT.35)   CALL FUSE(2,AID,RK,OFSET,TVAL1)
        IF(AID.GE.35)CALL
CKTBKR(2,IFIX(AID),RK,OFSET,TVAL1,REAL(
        1AIDEV(IEL,5)))
                        CUR=(10**RK)/(10**(REAL(AIDEV(IEL,3))
))
                        CALL
RELAY(MDEV,CUR,TVAL2,TMSET,DEV,0.0)
                        TIMEO=10**TVAL1+.4
                        TIMER=TVAL2
                        TIMES=ALOG10(TIMEO)
                        TMSET1=TIMES-TIMER
                        IF(TMSET1.LE.0)GO TO 20
                        TMSET=TMSET+TMSET1
20              CONTINUE
25              GO TO 30
30      CONTINUE
        AIDEV(IEL,6)=CMPLX(0.0,TMSET)
        TMSET=0.0
        GO TO 45
32      AID=AIMAG(AIDEV(IEL,2))
        FALT2=ALOG10(FALT1)
        IF(AID.GT.0)GO TO 35
        FALT1=FALT1*(EB1/EB2)
        IF(AID.LT.0)FALT=FALT1/(10**(REAL(AIDEV(IEL,4))))
        NDEV=-IFIX(AIMAG(AIDEV(IEL,2)))
        KFAL=IFIX(FALT*10)
        DIF=KFAL-15
        ID=IFIX(DIF/50)
        IF(ID.LE.0)ID=1
        DO 33 K=15,KFAL,ID
                RK=K*.1
        RK2=RK*(EB2/EB1)*(10**(REAL(AIDEV(IEL,4)))/10**
        1(REAL(AIDEV(IEL,3))))
                IF(RK.GT.20)GO TO 34
                CALL
RELAY(NDEV,RK,TVAL1,AIMAG(AIDEV(IEL,6)),DEV,
        1AIMAG(AIDEV(IEL,5)))
                CALL RELAY(MDEV,RK2,TVAL2,TMSET,DEV,0.0)
                TIMEO=10**TVAL1+.4
                TIMES=ALOG10(TIMEO)
                TIMER=TVAL2
```

```
                TMSET1=TIMES-TIMER
                IF(TMSET1.LE.0)GO TO 33
                TMSET=TMSET1+TMSET
33      CONTINUE
34      AIDEV(IEL,6)=AIDEV(IEL,6)+CMPLX(TMSET,0.0)
35      TMSET=0.0
        IF(AID.LT.0)GO TO 45
        OFSET=AIMAG(AIDEV(IEL,4))
        FNSET=FALT2-OFSET
        IF(FNSET.GT.1.5)FALT2=OFSET+1.5
        KVAL=IFIX(10*OFSET)
        KFAL=IFIX(10*FALT2)
        DO 40 K=KVAL,KFAL
                RK=K*.1
        IF(AID.LT.35)CALL FUSE(2,AID,RK,OFSET,TVAL1)
        IF(AID.GE.35)CALL
CKTBKR(2,IFIX(AID),RK,OFSET,TVAL1,AIMAG(
        1AIDEV(IEL,5)))
                CUR=RK-REAL(AIDEV(IEL,3))
                CURTA=10**CUR
                CUR=(EB2/EB1)*(10**RK)
                CURTA=CUR/(10**(REAL(AIDEV(IEL,3))))
                IF(CURTA.LT.1.5)GO TO 40
                CALL RELAY(MDEV,CURTA,TVAL2,TMSET,DEV,0.0)
                TIMEO=10**TVAL1+.4
                TIMER=TVAL2
                TIMES=ALOG10(TIMEO)
                TMSET1=TIMES-TIMER
                IF(TMSET1.LE.0)GO TO 40
                TMSET=TMSET+TMSET1
40      CONTINUE
        AIDEV(IEL,6)=AIDEV(IEL,6)+CMPLX(TMSET,0.0)
45      TMSET=0.0
        IF(JJ.EQ.0.AND.FALT1.GT.6)FALT1=6
        IF(IL.EQ.0.AND.JJ.EQ.0)AIDEV(IEL,5)=CMPLX(0.0,FALT1)
        FALT1=FALT1/(10**REAL(AIDEV(IEL,3)))
        IF(FALT1.GT.6)FALT1=6
        IF(IL.EQ.0.AND.JJ.NE.0)AIDEV(IEL,5)=AIDEV(IEL,5)+CMPL
X(FALT1,
        10.0)
100     RETURN
        END
*************************************************
C       SUBROUTINE SFALT1;PROVIDES THE DEVICE WITH THE
LONGEST
C               TIME AT FAULT,FIRST DEV IN ELEMENT.
*************************************************
        SUBROUTINE SFALT1(AIDEV,CUREL,RID,IEL,I,J,TVAL,DEV,
        1CVAL)
```

```
      DIMENSION AIDEV(100,6),CUREL(100),RID(100),IID(3),
      1IIDD(30),DEV(20,0/4)
      COMPLEX AIDEV,CUREL,RID
      DO 10 JI=1,30
            CALL SERCH(1,RID,IEL,J,JI,IA,IID)
            IF(IA.EQ.0)GO TO 10
            DO 8 JA=1,IA
                  IN=IN+1
                  IIDD(IN)=IID(IA)
8           CONTINUE
10    CONTINUE
      DO 30 INN=1,IN
            ID=IIDD(INN)
            IJ=IFIX(AIMAG(RID(ID)))
            CURJ=AIMAG(CUREL(ID))
            CALL REFALT(IJ,ID,FALT,CURJ)
            FALT2=ALOG10(FALT)
            AID=REAL(AIDEV(ID,2))
            IAID=IFIX(AID)
            IF(IAID.GT.32)GO TO 100
            FALT2=REAL(AIDEV(IEL,4))+.5
            FALT0=10**(FALT2)
            IF(IAID.LT.0)FALT=FALT0/(10**(REAL(AIDEV(ID,3
))))
            NDEV=-IFIX(REAL(AIDEV(ID,2)))
            IF(IAID.LT.0)CALL RELAY(NDEV,FALT,TVAL1,REAL
      1(AIDEV(ID,6)),DEV,REAL(AIDEV(ID,5)))
            FAL=REAL(AIDEV(IEL,4))+.5
            IF(FAL.LT.FALT2)FALT2=FAL
            IF(IAID.GT.0)CALL
FUSE(2,AID,FALT2,AIMAG(AIDEV
      1(ID,3)),TVAL1)
            IF(TVAL.GE.TVAL1)GO TO 25
            GO TO 30
25          IF(IAID.LT.0)CVAL=-FALT2
            CVAL=FAL
            TVAL=TVAL1
30    CONTINUE
100   RETURN
      END
**************************************************
**************************************************
C     SUBROUTINE SFALT2;AS IN 1,COMPUTES TIME FOR LOAD
SIDE OF
C           ELEMENT AT FALT.
**********************************************
      SUBROUTINE SFALT2(AIDEV,IEL,I,J,TVAL1,DEV,FALT,CVAL)
      DIMENSION AIDEV(100,6),DEV(20,0/4)
      COMPLEX AIDEV
```

```
          FALT2=ALOG10(FALT)
          AID=AIMAG(AIDEV(IEL,2))
          FAL=REAL(AIDEV(IEL,3))+.5
          FALT=10**(FAL)
          FALT3=FALT/(10**(AIMAG(AIDEV(IEL,3))))
          IF(AID.LT.0)CALL
     RELAY(NDEV,FALT3,TVAL1,AIMAG(AIDEV(IEL
          1,6)),DEV,AIMAG(AIDEV(IEL,5)))
          IF(FAL.LT.FALT2)FALT2=FAL
          IF(AID.GT.0)CALL FUSE(2,AID,FAL,AIMAG(AIDEV(IEL,4))
          1,TVAL1)
          CVAL=FALT2
          RETURN
          END
     ************************************************
     ************************************************
          SUBROUTINE XFDEV(NN,I,IEL,AIDEV,COOF)
          DIMENSION IID(30),AIDEV(100,6)
          COMPLEX AIDEV
          COOF=0.0
          IX=0
          IF(NN.NE.1)GO TO 50
          DO 30 IA=1,100
                    AID=REAL(AIDEV(IA,1))
                    IF(IFIX(AID).NE.I)GO TO 30
                    IX=IX+1
                    IID(IX)=IA
     30   CONTINUE
          DO 32 K=1,IX
     32   CONTINUE
          DO 40 JA=1,IX
                    OFSET=AIMAG(AIDEV(IID(JA),3))
                    IF(REAL(AIDEV(IID(JA),2)).LT.0)OFSET=REAL(AID
     EV(
          1IID(JA),3))
                    IF(REAL(AIDEV(IID(JA),2)).GE.35)OFSET=REAL(AI
     DEV(
          1IID(JA),5))+OFSET-.05
                    IF(AIMAG(AIDEV(IEL,2)).LT.0.AND.REAL(AIDEV(II
     D
          1(JA),2)).GT.0.AND.REAL(AIDEV(IID(JA),2)).LT.35)
          2OFSET=OFSET+.15
                    IF(COOF.GT.OFSET)GO TO 40
                    COOF=OFSET
     40   CONTINUE
          GO TO 60
     50   IF(AIMAG(AIDEV(IEL,2)).GT.0)COOF=AIMAG(AIDEV(IEL,4))
          IF(AIMAG(AIDEV(IEL,2)).LT.0)COOF=REAL(AIDEV(IEL,4))
          IF(AIMAG(AIDEV(IEL,2)).GE.35)COOF=AIMAG(AIDEV(IEL,5))
```

```
-.075
          1+COOF
          IF(REAL(AIDEV(IEL,2)).LT.0.AND.AIMAG(AIDEV(IEL,2)).GT
.0
          1.AND.AIMAG(AIDEV(IEL,2)).LT.35)COOF=COOF+.15
60        COOF=COOF+.025
          DOOF=10**(COOF)
          COOF=DOOF
          RETURN
          END
**************************************************
**************************************************
C         SUBROUTINE SETCKB;CORDINATES AND SELECTS A THERMAL
MAGNETIC
C                   BREAKER.
**************************************************
**************************************************
          SUBROUTINE SETCKB(CUREL,I,JJ,IEL,AIDEV,IDEV,OFSET
          1,OFSET1,AMAG,EB1,EB2)
          DIMENSION AIDEV(100,7),CON(5)
          COMPLEX AIDEV,CUREL
          CON(1)=2.6
          CON(2)=3.5
          CON(3)=5.0
          CON(4)=6.0
          CON(5)=7.0
          J=IFIX(AIMAG(AIDEV(IEL,1)))
          IF(J.EQ.0)CALL XFDEV(1,J,IEL,AIDEV,COOF)
          IF(J.NE.0)CALL XFDEV(2,J,IEL,AIDEV,COOF)
          IF(J.EQ.0)DOOF=ALOG10(COOF)-AIMAG(AIDEV(IEL,5))
          IF(J.EQ.0)COOF=10**DOOF
          IF(J.NE.0)DOOF=ALOG10(COOF)-AIMAG(AIDEV(IEL,5))
          IF(J.NE.0)COOF=10**DOOF
          IF(J.EQ.0)CURR=AIMAG(CUREL)
          IF(J.NE.0)CURR=REAL(CUREL)
          IF(EB1.NE.EB2)GO TO 45
          IF(COOF.LT.CURR)COOF=CURR
          GO TO 46
45        RE2=(EB2/EB1)*COOF
          IF(RE2.GE.CURR)COOF=RE2
          IF(RE2.LT.CURR)COOF=CURR
46        CALL SBRKR(COOF,IDEV3,OFSET,OFSET1,DMMY)
          IF(IDEV.LT.IDEV3)IDEV=IDEV3
          IF(IDEV.GE.IDEV3)IDEV=IDEV+1
          CI=I
          CJ=JJ
          AIDEV(IEL,1)=CMPLX(CI,CJ)
          IF(J.EQ.0)AIDEV(IEL,2)=CMPLX(0.0,FLOAT(IDEV))
          IF(J.NE.0)AIDEV(IEL,2)=CMPLX(FLOAT(IDEV),0.0)+AIDEV
```

```
          1(IEL,2)
          IF(J.EQ.0)AIDEV(IEL,4)=CMPLX(OFSET,OFSET1)
          IF(J.NE.0)AIDEV(IEL,3)=CMPLX(OFSET,OFSET1)
          IF(J.EQ.0)FLT=4*AIMAG(CUREL)
          IF(J.NE.0)FLT=4*REAL(CUREL)
          SET=10**(OFSET-.12)
          DO 50 K=1,5
                  TRP=CON(K)*SET
                  IF(TRP.GT.FLT)GO TO 60
50        CONTINUE
60        IF(AMAG.NE.0)AMAG=ALOG10(CON(K))
          IF(J.EQ.0)AIDEV(IEL,5)=CMPLX(0.0,AMAG)
          IF(J.NE.0)AIDEV(IEL,5)=CMPLX(AMAG,0.0)+AIDEV(IEL,5)
          RETURN
          END
**************************************************
**************************************************
C         SUBROUTINE SELECT;SELECTS A PARTICULAR DEVICE
**************************************************
          SUBROUTINE SELECT(CURLO,EB,ADEVL1,ADEVL2,ADEVL3,CT)
          IDEVL1=IFIX(ADEVL1)
54        IF(IDEVL1.EQ.0)GO TO 99
          IF(IDEVL1.EQ.1)GO TO 60
          IF(IDEVL1.EQ.2)GO TO 70
          IF(IDEVL1.EQ.4)GO TO 80
          IF(IDEVL1.GT.4)GO TO 53
          GO TO 58
53        TYPE 55
55        FORMAT(' NO SUCH DEVICE OR DEVICE ERROR, RE-ENTER
          1 DEVICE NR 1-4..,'$)
          ACCEPT 56, IDEVL1
56        FORMAT(I)
          GO TO 54
58        IF(EB.GT.600.0) GO TO 53
          CALL SBRKR(CURLO,IDEVL1,ADEVL2,ADEVL3,ADEVL4)
          ADEVL1=FLOAT(IDEVL1)
          CT=ADEVL4
          GO TO 100
60        CALL SFUSE(CURLO,IDEVL1,ADEVL2,ADEVL3)
          ADEVL1=FLOAT(IDEVL1)
          GO TO 100
70        IF(EB.LT.600)GO TO 53
          CALL SBORFU(CURLO,IDEVL1,ADEVL2,ADEVL3)
          ADEVL1=FLOAT(IDEVL1)
          GO TO 100
80        CALL SRELA(CURLO,IDEVL1,NTAP,NCT,PKUP,CT)
          ADEVL1=IDEVL1
          ADEVL2=PKUP
          ADEVL3=NCT*100+NTAP
```

```
      GO TO 100
99    ADEVL1=99
      ADEVL2=CURLO
      ADEVL3=CURLO
100   CONTINUE
      RETURN
      END
*****************************************************
C     SUBROUTINE SFUSE;USED TO SELECT A CURRENT LIMITING
FUSE
C           THIS MAY BE EITHER HIGH OR LOW VOLTAGE
*****************************************************
      SUBROUTINE SFUSE(CURLO,NDEV,OFSET,OFSET1)
      IF(NDEV.LT.0)GO TO 10
      DEV=-11.15221+(23.865*ALOG10(CURLO))-(16.487*(ALOG10(
CURLO
     1)**2))+(2.9288*(ALOG10(CURLO)**3))+(3.19672*(ALOG10(
CU
     2RLO)**4))-(1.48877*(ALOG10(CURLO)**5))+(.1776431*(AL
OG
     310(CURLO)**6))
      NDEV=IFIX(DEV)+1
      IF(NDEV.GT.15)NDEV=15
10    DEV=ABS(FLOAT(NDEV))
      OFSET=.9532-(.046433*DEV)+(.117885*(DEV**2))+(-.02935
2*(DEV
     1**3))+(.00337*(DEV**4))+(-.0001847*(DEV**5))+(.00000
39*(
     2DEV**6))
      OFSET1=OFSET+.1
      IF(NDEV.LT.-15)NDEV=-15
      IF(NDEV.GT.15)NDEV=15
      RETURN
      END
*****************************************************
C     SUBROUTINE SBORFU;USED TO SELECT A BORIC ACID HIGH
VOLTAGE
C           FUSE
*****************************************************
      SUBROUTINE SBORFU(CURLO,NDEV,OFSET,OFSET1)
      ALOGC=ALOG10(CURLO)
      IF(NDEV.LT.0)GO TO 10
      DEV=88.1643+(-215.2235*(ALOGC))+(188.225*(ALOGC**2))+
(-69.
     13463*(ALOGC**3))+(7.4695*(ALOGC**4))+(1.65257*(ALOGC
**5))+
     2(-.347786*(ALOGC**6))
      NDEV=IFIX(DEV)+1
      IF(NDEV.GT.19)NDEV=19.
```

```
10        DEV=ABS(FLOAT(NDEV))
          IF(NDEV.LT.0)DEV=DEV-15
          OFSET=1.366111+.1134579*DEV+(-.0012654*(DEV**2))+(.00
00213*
          1(DEV**3))
          OFSET1=OFSET+.1
          IF(NDEV.LT.-19)NDEV=-19
          IF(NDEV.GT.19)NDEV=19
          IF(NDEV.LT.0)NDEV=-NDEV+15
          IF(NDEV.GT.0)NDEV=NDEV+15
          RETURN
          END
**************************************************
C         SUBROUTINE SBRKR;USED TO SELECT A THERMAL MAGNETIC
BREAKER
**************************************************
          SUBROUTINE SBRKR(CURLO,NDEV,OFSET,OFSET1,AMAG)
          DIMENSION CON(5)
          CON(1)=2.6
          CON(2)=3.5
          CON(3)=4.6
          CON(4)=5.6
          CON(5)=7.0
          TYPE 10
10        FORMAT(' ENTER MANUFACTURER  (N.A. AT PRESENT USE
FOR FUTURE
          1EXPANSION)')
          TYPE 25
25        FORMAT(' INPUT TEMPERATURE FOR AMBIENT SHIFT,1 FOR
LESS THAN
          110 DEG C,2 FOR 60 DEG C,'//'<CR>FOR NO SHIFT..')
          ACCEPT 28,IOFF
28        FORMAT(I)
          IF(IOF.EQ.1)OFS=-.1
          IF(IOF.EQ.2)OFS=.05
          IF(MAN.NE.0)GO TO 80
          IF(CURLO.LE.600.)GO TO 30
          IF(CURLO.LE.800.)GO TO 50
          GO TO 70
30        IF(CURLO.LT.300.)MDEV=1
          IF(CURLO.LT.300.)OFSET=2.47712
          IF(CURLO.GT.300.0.AND.CURLO.LE.350.)MDEV=2
          IF(CURLO.GT.300.0.AND.CURLO.LE.350.)OFSET=2.54407
          IF(CURLO.GT.350.0.AND.CURLO.LE.400.)MDEV=3
          IF(CURLO.GT.350.0.AND.CURLO.LE.450.)OFSET=2.60206
          IF(CURLO.GT.400.0.AND.CURLO.LE.450.)MDEV=4
          IF(CURLO.GT.400.0.AND.CURLO.LE.450.)OFSET=2.65321
          IF(CURLO.GT.450.0.AND.CURLO.LE.500.)MDEV=5
          IF(CURLO.GT.450.0.AND.CURLO.LE.500.)OFSET=2.69897
```

```
      IF(CURLO.GT.500.)MDEV=6
      IF(CURLO.GT.500.)OFSET=2.77815
      GO TO 80
50    IF(CURLO.LE.700.)MDEV=7
      IF(CURLO.LE.700.)OFSET=2.8451
      IF(CURLO.GT.700.)MDEV=8
      IF(CURLO.GT.700.)OFSET=2.90309
      GO TO 80
70    IF(CURLO.LE.1000.)MDEV=9
      IF(CURLO.LE.1000.)OFSET=3.0
      IF(CURLO.GT.1000.)MDEV=10
      IF(CURLO.GT.1000.)OFSET=3.3
80    NDEV=MDEV+34
      OFSET=OFSET+OFS+.1122
      OFSET1=OFSET+.12
      TYPE 90
90    FORMAT(' DOES THE DEVICE HAVE A MAGNETIC
ELEMENT?(0)YES.')
      ACCEPT 95,NOEL
95    FORMAT(I)
      FCUR=4*CURLO
      SET=10**(OFSET-.12)
      DO 100 I=1,5
            TD=SET*CON(I)
            IF(TD.GT.FCUR)GO TO 105
100   CONTINUE
105   AMAG=ALOG10(CON(I))
      IF(NOEL.NE.0)AMAG=0.0
      RETURN
      END
*****************************************************
C     SUBROUTINE SRELA;USED TO SELECT A RELAY
*****************************************************
      SUBROUTINE SRELA(CURLO,NDEV,NTAP,NCT,PKUP,CT)
      TYPE 10
10    FORMAT(' SELECT MANUFACTUER  (FUTURE EXPANSION)')
      TYPE 20
20    FORMAT(' SELECT THE WESTINGHOUSE CO RELAY  ,REFER TO
TABLE',$)
      ACCEPT 25,NUM
25    FORMAT(I)
      NDEV=-NUM
      IF(CURLO.LT.30)CT=10
      IF(CURLO.GE.30.AND.CURLO.LT.120)CT=30
      IF(CURLO.GE.120)CT=120
      IF(CT.EQ.10)NCT=1
      IF(CT.EQ.30)NCT=2
      IF(CT.EQ.120)NCT=3
      TAP=CURLO/CT
```

```
      IF(TAP.LE.1.0)GO TO 71
      IF(TAP.LE.1.2)GO TO 72
      IF(TAP.LE.1.5)GO TO 73
      IF(TAP.LE.2.0) GO TO 74
      IF(TAP.LE.2.5)GO TO 75
      IF(TAP.LE.3.0)GO TO 76
      IF(TAP.LE.3.5)GO TO 77
      IF(TAP.LE.4.0)GO TO 78
      IF(TAP.LE.5.0)GO TO 79
      IF(TAP.LE.6.0)GO TO 80
      IF(TAP.LE.7.0)GO TO 81
      IF(TAP.LE.8.0)GO TO 82
      IF(TAP.LE.10.0)GO TO 83
      GO TO 84
71    NTAP=1
      TAP=1.0
      GO TO 90
72    NTAP=2
      TAP=1.2
      GO TO 90
73    NTAP=3
      TAP=1.5
      GO TO 90
74    NTAP=4
      TAP=2.0
      GO TO 90
75    NTAP=5
      TAP=2.5
      GO TO 90
76    NTAP=6
      TAP=3.0
      GO TO 90
77    NTAP=7
      TAP=3.5
      GO TO 90
78    NTAP=8
      TAP=4.0
      GO TO 90
79    NTAP=9
      TAP=5.0
      GO TO 90
80    NTAP=10
      TAP=6.0
      GO TO 90
81    NTAP=11
      TAP=7.0
      GO TO 90
82    NTAP=12
      TAP=8.0
```

```
      GO TO 90
83    NTAP=13
      TAP=10.0
      GO TO 90
84    NTAP=14
      TAP=12.0
90    PKUP=ALOG10(TAP*CT)
      RETURN
      END
```

```
C       TITLE:PLOTD.F4;PLOTS DEVICES FROM COORD.F4
*****************************************************
        OPEN(UNIT=30,FILE='ADEV.DAT')
        OPEN(UNIT=31,FILE='DEV.DAT')
        OPEN(UNIT=32,FILE='RELA.DAT')
        OPEN(UNIT=33,FILE='FCUR.DAT')
        OPEN(UNIT=34,FILE='TEST.DAT')
        EXTERNAL T25HAN
        DIMENSION EB(30),DEV(20,0/4),AIDEV(100,7),RID(100)
        COMPLEX AIDEV,RID
        READ(32,3)R
3       FORMAT(F)
5       READ(32,10)I
10      FORMAT(I)
        IF(I.NE.0)GO TO 5
15      READ(32,20)I,E1
20      FORMAT(I,F)
        IF(I.EQ.0)GO TO 25
        EB(I)=E1
        GO TO 15
25      DO 40 K=1,100
        READ(30,30)I,(AIDEV(I,J),J=1,7)
30      FORMAT(I,14F)
        IF(I.EQ.0)GO TO 45
40      CONTINUE
45      READ(34,50)IB,E1
50      FORMAT(I,F)
55      READ(34,60)NN,I,J,K,R,X
60      FORMAT(4I,2F)
        IF(NN.EQ.0) GO TO 70
        NE=NN
        CI=I
        CJ=J
        RID(NN)=CMPLX(CI,CJ)
        GO TO 55
70      DO 80 I=1,20
                READ(31,75)K,(DEV(I,J),J=0,4)
75      FORMAT(I,5F)
        IF(K.EQ.0)GO TO 400
80      CONTINUE
400     TYPE 410
410     FORMAT(' DEVICE LISTING')
        DO 440 I=1,NE
        TYPE 420,I,(AIDEV(I,J),J=1,7)
        PRINT 420,I,(AIDEV(I,J),J=1,7)
420     FORMAT(I,14F)
440     CONTINUE
445     TYPE 450
450     FORMAT(' DEVICES HAVE BEEN SET IF YOU WANT TO PLOT
```

```
GRAPH PAPER
        1 ENTER(0),IF NOT TYPE(1)')
        ACCEPT 456,IP
456     FORMAT(I)
        IF(IP.NE.0)GO TO 480
        TYPE 460
460     FORMAT(' THIS WILL PLOT CURVES BASED TO THE LOWEST
VOLTAGE
        1 IN THE SYSTEM.')
        TYPE 461
461     FORMAT(' INPUT THE CURRENT OFFSET FOR THE
GRAPH,INTEGER..')
        ACCEPT 462,IAOFF
462     FORMAT(I)
        CALL INITT
        CALL LOG(IAOFF)
        CALL FLUSH
480     TYPE 485
485     FORMAT(' INPUT ELEMENT  ..')
        ACCEPT 490,IEL
490     FORMAT(I)
        I=IFIX(REAL(RID(IEL)))
        J=IFIX(AIMAG(RID(IEL)))
        EB1=EB(1)
        DO 495 K=1,IB
                EB1=AMIN1(EB1,EB(K))
495     CONTINUE
550     FAC=ALOG10(EB(I)/EB1)-IAOFF
        FAC1=ALOG10(EB(J)/EB1)-IAOFF
        CUR=REAL(AIDEV(IEL,3))
        CUR1=REAL(AIDEV(IEL,4))
        CUR2=AIMAG(AIDEV(IEL,3))
        CUR3=AIMAG(AIDEV(IEL,4))
*****************************************************
C       NOW TO PLOT LOAD SIDE OF THE ELEMENT
*****************************************************
        CALL REFALT(J,IEL,FALT,900.0)
        IF(AIMAG(AIDEV(IEL,2)).GT.0) GO TO 585
        STL=REAL(AIDEV(IEL,4))
        STP=FALT/10**STL
        IF(AIMAG(AIDEV(IEL,5)).NE.0)STP=AIMAG(AIDEV(IEL,5))
        ST1=ALOG10(FALT)
        YM=(STL+FAC1)*190+175.0
        XM=0.0
        CALL MOVEA(XM,YM)
        STP=10*STP
        ITP=IFIX(STP)
        IF(ITP.LT.15) TYPE 575
575     FORMAT(' THE LOAD SIDE RELAY WILL NOT BE VERY
```

```
SENSITIVE
        1 TO A FAULT')
        IDEV=IFIX(ABS(AIMAG(AIDEV(IEL,2))))
        TYPE 570,IDEV,ITP
570     FORMAT(' IDEV,',2I)
        DIF=ITP-15.
        ID=IFIX(DIF/200.0)
        IF(ID.LE.0)ID=1
        TVAL3=10.0
        TDSET=AIMAG(AIDEV(IEL,6))
        DO 580 K=15,ITP,ID
                RK=.1*(FLOAT(K))
                CALL RELAY(IDEV,RK,TVAL,TDSET,DEV)
                IF(TVAL.GT.TVAL3)TVAL=TVAL3
                TVAL3=TVAL
                T=900-((TVAL+2.0)*180)
                R=(ALOG10(RK)+FAC1+STL)*190+175.0
                CALL DRAWA(T,R)
580     CONTINUE
        PAUSE 4
        IF(AIMAG(AIDEV(IEL,5)).NE.0)CALL DRAWA((900.0),R)
        GO TO 591
585     OFSET=CUR1
        M=IFIX(80*OFSET)
        ADEV=AIMAG(AIDEV(IEL,2))
        KIM=IFIX(100*(ALOG10(FALT)))
        DO 587 K=M,KIM
                CVAL=K*.01
        IF(ADEV.LT.35)CALL FUSE(1,ADEV,CVAL,OFSET,TVAL)
        IF(ADEV.GE.35)CALL
CKTBKR(1,IFIX(ADEV),CVAL,OFSET,TVAL,
        1AIMAG(AIDEV(IEL,5)))
                TVAL=TVAL+2.0
                IF(TVAL2.LT.TVAL.AND.ND.NE.0)GO TO 589
                TVAL2=TVAL
                ND=1
                CALL
DRAWA(900-((TVAL)*180),(CVAL+FAC1)*190+175.0)
587     CONTINUE
589     OFSET=CUR3
        CALL MOVEA(0.0,0.0)
        ND=0
        M=IFIX(80*OFSET)
        DO 588 K=M,KIM
                CVAL=K*.01
        IF(ADEV.LT.35)CALL FUSE(2,ADEV,CVAL,OFSET,TVAL)
        IF(ADEV.GE.35)CALL
CKTBKR(2,IFIX(ADEV),CVAL,OFSET,TVAL,
        1AIMAG(AIDEV(IEL,5)))
```

```
                TVAL=TVAL+2.0
                IF(TVAL2.LT.TVAL.AND.ND.NE.0)GO TO 591
                TVAL2=TVAL
                ND=1
                CALL
DRAWA(900-((TVAL)*180),(CVAL+FAC1)*190+175.0)
588     CONTINUE
*****************************************************
C       NOW TO DRAW THE LINE SIDE
*****************************************************
591     CALL MOVEA(0.0,0.0)
        AID=(REAL(AIDEV(IEL,2)))
        IF(AID.GT.0)GO TO 595
        IDEV=IFIX(-AID)
        STL=REAL(AIDEV(IEL,3))
        STP=FALT/10**STL
        IF(REAL(AIDEV(IEL,5)).NE.0)STP=REAL(AIDEV(IEL,5))
        YM=(STL+FAC)*190+175.0
        XM=0.0
        CALL MOVEA(XM,YM)
        STP=STP*10
        ITP=IFIX(STP)
        DIF=ITP-15
        ID=IFIX(DIF/200.0)
        LF(ID.LE.0)ID=1
        TVAL3=10.0
        TDSET=REAL(AIDEV(IEL,6))
        DO 590 K=15,ITP,ID
                RK=K*.1
                CALL RELAY(IDEV,RK,TVAL,TDSET,DEV)
                IF(TVAL.GT.TVAL3)TVAL=TVAL3
                TVAL3=TVAL
                CALL
DRAWA(900-((TVAL+2.0)*180),((ALOG10(RK)+STL
        1+FAC)*190+175.0))
590     CONTINUE
        IF(REAL(AIDEV(IEL,5)).NE.0)CALL
DRAWA((900.0),((ALOG10(RK)+
        1STL+FAC)*190+175))
595     IF(REAL(AIDEV(IEL,2)).LT.0)GO TO 598
        OFSET=CUR
        ADEV=REAL(AIDEV(IEL,2))
        ND=0
        M=IFIX(80*OFSET)
        KIM=IFIX(100*ALOG10(FALT))
        DO 597 K=M,KIM
                CVAL=K*.01
        IF(ADEV.LE.34)CALL FUSE(1,ADEV,CVAL,OFSET,TVAL)
        IF(ADEV.GE.35)CALL
```

```
CKTBKR(1,IFIX(ADEV),CVAL,OFSET,TVAL,
     1REAL(AIDEV(IEL,5)))
              TVAL=TVAL+2.0
              IF(TVAL2.LT.TVAL.AND.ND.NE.0)GO TO 601
              TVAL2=TVAL
              ND=1
              CALL
DRAWA(900-(TVAL*180),(CVAL+FAC)*190+175.0)
597     CONTINUE
601     OFSET=CUR2
        CALL MOVEA(0.0,0.0)
        ND=0
        M=IFIX(80*OFSET)
        DO 599 K=M,KIM
              CVAL=K*.01
        IF(ADEV.LE.34)CALL FUSE(2,ADEV,CVAL,OFSET,TVAL)
        IF(ADEV.GE.35)CALL
CKTBKR(2,IFIX(ADEV),CVAL,OFSET,TVAL,
     1REAL(AIDEV(IEL,5)))
              TVAL=TVAL+2.0
              IF(TVAL2.LT.TVAL.AND.ND.NE.0)GO TO 598
              TVAL2=TVAL
              ND=1
              CALL
DRAWA(900-(TVAL*180),(CVAL+FAC)*190+175.0)
599     CONTINUE
598     TYPE 600
600     FORMAT(' FINISHED??')
        ND=0
        CALL MOVEA(0.0,0.0)
        CALL FLUSH
        ACCEPT 610,I
610     FORMAT(I)
        IF(I.EQ.0)GO TO 2000
        GO TO 445
2000    CLOSE(UNIT=30)
        CLOSE(UNIT=31)
        CLOSE(UNIT=32)
        CLOSE(UNIT=33)
        CLOSE(UNIT=34)
        CALL FINITT(0,0)
        STOP
        END
*****************************************************
C       SUBROUTINE REFALT;READS FCUR.DAT TO OUTPUT FAULT
CURRENTS
C               AT THE BUSSES
*****************************************************
        SUBROUTINE REFALT(IFALT,NEL,FALT,CUREL)
```

```
10      READ(33,15)IEF,NN,TFAL,SFAL
15      FORMAT(2I,2F)
        IF(IEF.EQ.0)GO TO 20
        IF(IEF.NE.IFALT)GO TO 10
        IF(NN.NE.NEL)GO TO 10
        FALT1=TFAL
        FALT2=SFAL
        FALT=AMIN1(FALT1,FALT2)
        FLOCUR=3.0*CUREL
        IF(FALT.LE.FLOCUR)FALT=AMAX1(FALT1,FALT2)
        FALT=AMAX1(FALT1,FALT2)
20      REWIND 33
        RETURN
        END
*****************************************************
C       SUBROUTINE FUSE;COMPUTES TIME VALUE FOR A GIVEN LOAD
CURRENT
*****************************************************
        SUBROUTINE FUSE(ID,ADEV,CVAL,OFSET,TVAL)
        TVAL=0.0
        IDEV=IFIX(ADEV)
        IF(IDEV.GT.15)GO TO 50
        X=CVAL-OFSET
        IF(ID.NE.1)GO TO 40
        TVAL=4.0480+(-36.4234*X)+(223.7526*(X**2))+(-751.279*
(X**3))
        1+(1347.01*(X**4))+(-1222.67*(X**5))+(440.813*(X**6))
        TVAL=TVAL-2.0
        GO TO 100
40      X=CVAL-OFSET+.1
        TVAL=6.426+(-37.922*X)+(121.909*(X**2))+(-213.420*(X*
*3))+
        1(201.771*(X**4))+(-96.9836*(X**5))+(18.6046*(X**6))
        TVAL=TVAL-2.0
        IF(X.GT.1.4)TVAL=-1.95
        GO TO 100
50      X=CVAL-OFSET
        IF(ID.NE.1)GO TO 70
        TVAL=3.876979+(-4.262768*X)+(1.21940*(X**2))
        TVAL=TVAL-2.0
        GO TO 100
70      X=CVAL-OFSET+.1
        TVAL=4.614841+(-6.173224*X)+(3.231806*(X**2))+(-.6057
136*(X**3))
        TVAL=TVAL-2.0
100     RETURN
        END
*****************************************************
C       SUBROUTINE RELAY;COMPUTES TIME VALUE FOR A GIVEN
```

```
CURRENT
C                VALUE FOR A SPECIFIC RELAY
**********************************************
         SUBROUTINE RELAY(NDEV,CURR,TVAL,TDSET,DEV)
         DIMENSION DEV(20,0/4)
         TVAL=0.0
         X=ALOG10(CURR)
         IF(X.GT.1.2)X=1.2
         DO 10 I=0,4
         TVAL=TVAL+DEV(NDEV,I)*(X**I)
10       CONTINUE
         IF(NDEV.EQ.7)TVAL=TVAL-2.0
         TVAL=TVAL+TDSET
         RETURN
         END
**********************************************************
C        TITLE:LOG.LOG,MAKES LOG LOG FORM FOR GRAPH OF RELAY
CURVES
**********************************************************
C        OUTLINE BORDER
**********************************************************
C        MUST USE ALOG.LOG,@SYS:GRALIB
**********************************************************
         SUBROUTINE LOG(IAOFF)
         CALL ERASE
         CALL MOVEA(0.0,0.0)
         CALL DRAWA(0.0,750.0)
         CALL DRAWA(1000.0,750.0)
         CALL DRAWA(1000.0,0.0)
         CALL DRAWA(0.0,0.0)
         CALL MOVEA(900.0,5.0)
         CALL DRAWA(900.0,750.0)
         DO 200 N=0,4
         DO 100 M=1,10
         DN=10**N
         XM=M*DN
         IF(XM.GT.35000) GO TO 225
         XX=(ALOG10(XM))*180
         XTT=900-XX
         CALL MOVEA(XTT,175.0)
         CALL DRAWR(0.0,575.0)
100      CONTINUE
200      CONTINUE
225      CALL MOVEA(900.0,175.0)
         CALL DRAWA(0.0,175.0)
         DO 400 N=0,2
         DO 300 M=1,10
         DN=10**N
         XM=M*DN
```

```
      XX=(ALOG10(XM))*190
      XT=XX+175
      CALL MOVEA(95.0,XT)
      CALL DRAWR(805.0,0.0)
300   CONTINUE
400   CONTINUE
      DO 460 M=0,3
      XN=175+190*M
      CALL MOVEA(900.0,XN)
      CALL NUMBER(10,'I2')
      CALL MOVER(0.0,10.0)
      J=IAOFF+M
      CALL NUMBER(J,'I1')
460   CONTINUE
      CALL CHRROT(90)
      CALL MOVEA(960.0,400.0)
      CALL ANCHOS('CURRE',5)
      CALL ANCHOS('NT I',4)
      CALL ANCHOS('N AMP',5)
      CALL ANCHOS('S',1)
      CALL MOVEA(900.0,0.0)
      CALL DRAWA(900.0,750.0)
      DO 500 M=0,5
      XN=900-180*M
      CALL MOVEA(XN,150.0)
      IF(M.EQ.0)CALL NUMBER(.01,'F3.2')
      IF(M.EQ.1)CALL NUMBER(.1,'F2.1')
      IF(M.EQ.2)CALL NUMBER(1,'I1')
      IF(M.EQ.3)CALL NUMBER(10,'I2')
      IF(M.EQ.4)CALL NUMBER(100,'I3')
      IF(M.EQ.5)GO TO 510
500   CONTINUE
510   CALL MOVEA(20.0,140.0)
      CALL NUMBER(1000,'I4')
      CALL CHRROT(0)
      CALL MOVEA(200.0,755.0)
      CALL ANCHOS('TIME ',5)
      CALL ANCHOS('IN SE',5)
      CALL ANCHOS('CONDS',5)
      CALL MOVEA(0.0,0.0)
      RETURN
      END
**************************************************
C     SUBROUTINE CKTBKR;COMPUTES TIME VALUE FOR A GIVEN
CURRENT
C                VALUE
**************************************************
      SUBROUTINE CKTBKR(ID,MDEV,DVAL,OFSET,TVAL,AMVAL)
      CVAL=DVAL-OFSET
```

```
      IF(ID.NE.1)GO TO 50
      CVAL=CVAL+.1122
      IF(CVAL.GT.AMVAL.AND.AMVAL.NE.0)GO TO 90
      IF(CVAL.LT.0)GO TO 80
      TVAL=5.76908+(-10.88261*(CVAL))+(23.65419*(CVAL**2))+
(-34.7922
      1*(CVAL**3))+(33.77472*(CVAL**4))+(-21.14536*(CVAL**5
))+(6.4
      231778*(CVAL**6))
      TVAL=TVAL-2.0
      GO TO 100
50    CVAL=CVAL+.232
      IF(CVAL.LT.0)GO TO 80
      AMVAL=AMVAL+.075
      IF(CVAL.GT.AMVAL.AND.AMVAL.NE.0)GO TO 95
      TVAL=5.8596722+(-4.394335*CVAL)+(-.50690284*(CVAL**2)
)+(10.40
      12739*(CVAL**3))+(-17.064956*(CVAL**4))+(13.011543*(C
VAL**5))
      2+(-4.010724*(CVAL**6))
      TVAL=TVAL-2.0
      GO TO 100
80    TVAL=6.0
      GO TO 150
90    TVAL=-2.0
      GO TO 100
95    TVAL=ALOG10(.025)
100   CONTINUE
150   RETURN
      END
*************************************************
```

APPENDIX C

DISK-FILE FORMATS

Disk file RES.DAT

a_o Double precision wire resistance coefficients

.
.

a_6 Double precision wire resistance coefficients

a_o Double precision wire reactance coefficients

.
.

a_6 Double precision wire reactance coefficients

Disk file TEST.DAT

element number/line bus/load bus/positive seq p.u. impedance/zero seq p.u. impedance/transformer neutral imp line bus/transformer neutral imp load bus

00000

Load data

bus number/p.u. VA/per unit subtransient reactance

0000

Disk file XFER.DAT

line bus/load bus/inrush/low withstand/high withstand/transformer size

LCUR.DAT

line bus/load bus/current at line bus/current at load bus

FCUR.DAT

fault bus/element number/3 phase fault/1 phase fault

DEV.DAT

device number/a_o/a_1/a_2/a_3/a_4

ADEV.DAT

element number/element bus numbers/device numbers/line bus element low pickup, high pickup/load bus element low pickup, high pickup/ magnetic settings line, load/time dial setting line, load/CT ratios line,load/

APPENDIX D

SAMPLE PROGRAM DATA INPUT

Before beginning the program sequence, RES.DAT and DEV.DAT contain the proper coefficients listed in Table 8.5. All source programs have been loaded and saved. PLOTD.F4 uses subroutines contained in the PDP10 system files so it must be loaded using:

LOAD PLOTD.F4, @ SYS:GRALIB.

The first program is started with run INPUT. Underlined words and numbers are data input by the user. Words not underlined are prompts from the computer in the input sequence that follows.

Do you want to read from a KYBRD?
<CR> for input from TTY, 1 for read. . .
<CR>

Enter the problem base in MVA
1

Enter the problem base in KV
15

Enter element data as follows: Bus ( ) to ( )
(Length)(Size)(Transformer impedance (P.U.))(Transformer size in MVA)(Transformer High Voltage in KV)(Transformer low voltage in KV)
1 2 3000 6 -(element with no transformer)
2 3 356 .001 .005 1 15 4.1 -(element with a transformer)
Input transformer ZN in P.U. refer to BUS

Side, (BUS 2) (BUS 3). . .
.001 .005 .001 .005

(This is continued for each element until all elements of the type in RES.DAT have been entered)

0 -(tells computer no more elements)

At this point if another wire type is to be used the following procedure applies if not skip this section and proceed to (1.)

```
Input Bus 1 voltage. . .0
Data is accepted and a list follows

       (Here the computer types all computed information on the
       elements entered so that they may be checked for error.)

Now enter the load data in the following manner;. . .
(Bus)(Load in KVA)(Pwr Factor). . .or. . .(Bus)(Load in HP)
(Pwr Factor). . .or. . .(Bus)(Load in Amps)(Pwr Factor)
What method will you use?. . .VA, HP, or Amps?
S -(writes element data computed to disk)
End of execution
(Load RES.DAT with the new wire type coefficients)
RUN INPUT
Do you want to read from a KYBRD?
<CR> for input from a TTY, 1 for read. . .  .
1
Old data is entered ready for new line data
Enter element data as follows. . .(Program runs as
       in the first section)

(1)    Picking up the program from completion of element data,
       the data entry follows.

Input Bus 1 Voltage. . .15000
Input Bus 2 Voltage. . .15000
Input Bus 3 Voltage. . .4100
      .
      .
Input Bus 8 Voltage. . .440
Data is accepted and a list follows
       (Computer types computed element data).

Number of buses is 8
Now enter the load data in the following manner;. . .
(Bus)(Load in KVA)(Pwr Factor). . .or. . .(Bus)(Load in HP)
(Pwr Factor). . .or. . .(Bus)(Load in Amps)(Pwr factor)
What method will you use?  KVA, HP, or Amps?
HP
Enter. . .
4 800 .80
What method will you use?. . .KVA, HP, or Amps?
HP
8 500 .90
       (This is continued until all loads are entered?
       What  method will you use?. . .KVA, HP, or Amps?
S
End of Execution
RUN LDFLO
End of Execution
RUN ZBUS
Enter the zero sequence impedance for the loads at each bus. . .
```

8 .001 .005 -for each load where the zero sequence impedance
: will not be assumed to equal the positive sequence
: impedance
0 -tells the computer there are no more entries
Enter the mutually coupled elements in per unit in the following format, TEST.DAT has the element numbers. . .,(Element)(Element) (Zero Sequence Value)
2 3 0 .001 (The zero must be entered because the coupling is a reactive value)
0 -(no more or no coupling)
End of execution
RUN FALT
Enter the fault impedance (Real)(Imaginary)
0 0
End of execution
RUN COORD
All load currents are ready, use device number list
Select device for the load at bus 4
4
:
:
Select the device for the load at Bus 8
3
Input temperature for ambient shift, 1 for less than
110 Deg C, 2 for 60 Deg C
<CR> for no shift. . .
<CR>
Does the device have a magnetic element?(0)Yes
0
Select device for Bus 6 protecting element feeding load at Bus 8
4
Select the Westinghouse Co. relay, refer to Table 1
Does the relay have an inst. element if yes 0
0
:
:

(Until all backup devices have been set).
Enter the device for the Bus 6 of element 5

4
Select the Westinghouse Co. relay, refer to Table 1
Does the relay have an inst. element if yes 0
0
:
:

(Until all devices in the system have been set).
Device listing -(Here the computer lists the matrix ADEV)
End of execution
Run PLOTD
Devices have been set if you want to plot graph paper 0 if not type 1
0

```
This will plot curves based on the lowest voltage in the
system
Input the current offset for the graph, integer 1
Input element number
7
Finished?
1 -(no, 0 yes)
Devices have been set if you want to plot graph paper
0 if not type 1
1
Input element number
6
Finished?
0
End of execution.
```

If a device did not plot as desired its settings can be changed in ADEV.DAT.

END

FILMED

11-83

DTIC